

A test for second order stationarity of a time series based on the Discrete Fourier Transform (Technical Report)

Yogesh Dwivedi and Suhasini Subba Rao

Texas A&M University,
College Station, Texas 77845, USA

November 25, 2009

Abstract

We consider a zero mean discrete time series, and define its discrete Fourier transform at the canonical frequencies. It is well known that the discrete Fourier transform is asymptotically uncorrelated at the canonical frequencies if and only if the time series is second order stationary. Exploiting this important property, we construct a Portmanteau type test statistic for testing stationarity of the time series. It is shown that under the null of stationarity, the test statistic is approximately a chi square distribution. To examine the power of the test statistic, the asymptotic distribution under the locally stationary alternative is established. It is shown to be a type of noncentral chi-square, where the noncentrality parameter measures the deviation from stationarity. The test is illustrated with simulations, where it is shown to have good power. Some real examples are also included to illustrate the test.

Keywords and phrases Discrete Fourier Transform, linear time series, local stationarity, Portmanteau test, test for second order stationarity.

1 Introduction

An important assumption that is often made when analysing time series is that it is at least second order stationary. Most of the linear time series literature is based on this assumption. If the assumption is not properly tested and the analysis is performed, the resulting models are considered to be misspecified and any forecasts obtained are not appropriate. Therefore, it is important to check whether the time series is second order stationary.

In recent years several statistical tests have been proposed. Many of the proposed tests are based on comparing spectral densities over various segments (Priestley and Subba Rao (1969), Picard (1985),

Giraitis and Leipus (1992), Adak (1998) and Paparoditis (2009)) comparing covariance structures over various segments of the data (Loretan and Philips (1994), Andreou and Ghysels (2008) and Berkes, Gombay, and Horváth (2009)), or comparisons of wavelet coefficients (Sachs and Neumann (1999), Cho and Fryzlewicz (2009)). The underlying important assumption, on which these tests are based, is on a delicate, subjective, choice of segments of the data. In this paper we propose a test based on the discrete Fourier transforms based on the entire length of data, thus avoiding a subjective choice of segment length.

In Section 2 we define the Discrete Fourier transform and show that the Discrete Fourier transforms are asymptotically uncorrelated at the canonical frequencies if and only if the time series is second order stationary. This motivates the test statistics, which is based on the discrete Fourier transform. The Portmanteau type test statistics we propose is based on the covariance function calculated using the discrete Fourier transform at the canonical frequencies. The asymptotic sampling distribution of the test statistic is obtained in Section 3. Further we show that the asymptotic sampling distribution is approximately distributed as a central chi-square under the null hypothesis that the time series is second order stationary. To examine the power of the test, we consider the case of locally stationary time series (see Subba Rao (1970), Ozaki and Tong (1975), Priestley (1981), Dahlhaus (1997), Nason and Sachs (1999), and Nason, Sachs, and Kroisandt (2000)), and derive the distribution of the test statistic under this class of alternatives. In Section 4 we show the distribution under this class of alternatives, is a type of non-central chi-square, where the noncentrality parameter is in some sense a measure of departure of nonstationarity. In Section 5, through simulations, we examine the power of the test, and show that for various types of alternatives the power is very high. We end this section with various comments on the types of nonstationary behaviour the test can detect. In Section 6 we illustrate the test with two real data examples.

An outline of important aspects of some proofs can be found in the appendix, and the full details can be found in the accompanying technical report.

2 The Test Statistic, motivation and sampling distribution

2.1 Motivation

Let $\{X_t\}$ be a zero mean time series. Suppose we observe $\{X_t; t = 1, \dots, T\}$ and let $J_T(\omega_k)$ be its Discrete Fourier Transform defined as

$$J_T(\omega_k) = \frac{1}{\sqrt{2\pi T}} \sum_{t=1}^T X_t \exp(it\omega_k), \text{ for } 1 \leq k \leq T,$$

where $\omega_k = \frac{2\pi k}{T}$ are the canonical frequencies. It is well known that if $\{X_t\}$ is a second order stationary time series, whose covariances are absolutely summable then for $k_1 \neq k_2$ and $k_1 \neq T - k_2$ we have $\text{cov}(J_T(\omega_{k_1}), J_T(\omega_{k_2})) = O(\frac{1}{T})$. Therefore in the case of stationary processes, the discrete Fourier transform $\{J_T(\omega_k)\}_{k=1}^T$ is asymptotically uncorrelated. Let

$$\kappa(t, \tau) = \mathbb{E}(X_t, X_\tau) = \frac{1}{T} \sum_{k_1, k_2=1}^T \mathbb{E}(J_T(\omega_{k_1}) \overline{J_T(\omega_{k_2})}) \exp(-it\omega_{k_1} + i\tau\omega_{k_2}),$$

where $\bar{z}$ is the complex conjugate of the complex variable z . From the above we observe if $\mathbb{E}(J_T(\omega_{k_1}) \overline{J_T(\omega_{k_2})}) = 0$ for $k_1 \neq k_2$ or $k_1 \neq T - k_2$, then we have $\kappa(t, \tau) = \kappa(t - \tau)$ for $0 \leq t, \tau \leq T - 1$. In other words, an uncorrelated discrete Fourier transform sequence implies that the original time series is second order stationary, up to lag T .

Let us consider a simple example to show that even if the time series are independent, but not stationary, then $\{J_T(\omega_k)\}$ are not uncorrelated. Let us suppose $X_t = \sigma_t \varepsilon_t$, where σ_t is a deterministic, time dependent function and $\{\varepsilon_t\}$ are independent identically distributed random variables with $\mathbb{E}(\varepsilon_t) = 0$ and $\text{var}(\varepsilon_t) = 1$. In this case, the covariance of the discrete Fourier transform at the canonical frequencies is

$$\text{cov}(J_T(\omega_{k_1}), J_T(\omega_{k_2})) = \frac{1}{2\pi T} \sum_{t=1}^T \sigma_t^2 \exp(it(\omega_{k_1} - \omega_{k_2})).$$

From the above, it is clear that $\text{cov}(J_T(\omega_{k_1}), J_T(\omega_{k_2})) \neq 0$ for some $k_1 \neq k_2$. If we suppose that σ_t is a sample from a smooth function $\sigma : [0, 1] \rightarrow \mathbb{R}$, that is $\sigma_t = \sigma(t/T)$, then by using the rescaling methods often used in nonparametric statistics we have

$$\text{cov}(J_T(\omega_{k_1}), J_T(\omega_{k_2})) = \int_0^1 \sigma(u)^2 \exp(i2\pi u(k_1 - k_2)) du.$$

2.2 The test statistic

The above observations lead us to the following test statistic. We note that, if the time series is second order stationary, then $\mathbb{E}(J_T(\omega_k)) = 0$ and $\text{var}(J_T(\omega_k)) \rightarrow f(\omega_k)$ as $T \rightarrow \infty$, where $f : [0, 2\pi] \rightarrow \mathbb{R}$ is the spectral density of the original time series $\{X_t\}$ (see Priestley (1981) and Brockwell and Davis (1987)). Therefore by standardising with $\sqrt{f(\omega_k)}$, under the null of stationarity, $\{J_T(\omega_k)/\sqrt{f(\omega_k)}\}$ is close to an uncorrelated, second order stationary sequence. Therefore to test for stationarity of $\{X_t\}$ we will test for randomness of the sequence $\{J_T(\omega_k)/\sqrt{f(\omega_k)}\}$. The proposed test will be a type of Portmanteau test (see Chen and Deo (2004) for applications of the Portmanteau test in time series analysis). Of course, in reality the spectral density $f(\omega)$ is unknown,

therefore we will replace $f(\cdot)$ with the estimated spectral density function $\hat{f}_T(\cdot)$, where

$$\hat{f}_T(\omega_k) = \sum_j \frac{1}{bT} K\left(\frac{\omega_k - \omega_j}{b}\right) |J_T(\omega_j)|^2, \quad (1)$$

$K : [-1/2, 1/2] \rightarrow \mathbb{R}$ is a positive, continuous, symmetric kernel function which satisfies $\int_{-1}^1 K(x) dx = 1$ and $\int_{-1}^1 K(x)^2 dx < \infty$ and b is a bandwidth.

We define the empirical covariance at lag r , which is complex valued, of the discrete Fourier transform as

$$\hat{c}_T(r) = \frac{1}{T} \sum_{k=1}^T \frac{J_T(\omega_k) \overline{J_T(\omega_{k+r})}}{\sqrt{\hat{f}_T(\omega_k) \hat{f}_T(\omega_{k+r})}}, \quad \text{for } 1 \leq r \leq T-1. \quad (2)$$

The proposed test statistic is based on $\hat{c}_T(r)$. In the technical report we show that if $\{X_t\}$ is a stationary time series and $\mathbb{E}(X_t^4) < \infty$ then both the variance of the real and imaginary parts of $\sqrt{T} \hat{c}_T(r)$ converge to

$$1 + \frac{1}{4\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{f_4(\lambda_1, -\lambda_1 - \omega_r, \lambda_2)}{\sqrt{f(\lambda_1) f(\lambda_1 + \omega_r) f(\lambda_2) f(\lambda_2 + \omega_r)}} d\lambda_1 d\lambda_2, \quad (3)$$

as $T \rightarrow \infty$, where $\omega_r = 2\pi r/T$, $f_4(\lambda_1, \lambda_2, \lambda_3) = (2\pi)^{-3} \sum_{j_1, j_2, j_3=-\infty}^{\infty} \text{cum}(X_0, X_{j_1}, X_{j_2}, X_{j_3}) \exp(i(\lambda_1 j_1 + \lambda_2 j_2 + \lambda_3 j_3))$ is the fourth order cumulant spectra. Furthermore, under the null hypothesis of second order stationarity, we show in Lemma 3.1, that the empirical covariances $\hat{c}_T(r)$ at different lags are asymptotically uncorrelated and $\hat{c}_T(r) = o_p(1)$. Therefore we define the test statistic

$$\mathcal{T}_m = T \sum_{n=1}^m \frac{|\hat{c}_T(r_n)|^2}{1 + \frac{1}{4\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{f_4(\lambda_1, -\lambda_1 - \omega_{r_n}, -\lambda_2)}{\sqrt{f(\lambda_1) f(\lambda_1 + \omega_{r_n}) f(\lambda_2) f(\lambda_2 + \omega_{r_n})}} d\lambda_1 d\lambda_2},$$

where $|z|^2 = z\bar{z}$ and $r_n \neq 0$ or $T/2$. For example, we can choose $r_n = n$, and use m consecutive lags. We note, that unlike the classical Portmanteau tests, using covariances with a large lag is not problematic as the discrete Fourier transform is periodic.

We derive the asymptotic distribution of the test statistic in Section 3, under the null hypothesis that $\{X_t\}$ satisfies the MA(∞) representation

$$X_t = \sum_{j=0}^{\infty} \psi_j \varepsilon_{t-j}, \quad (4)$$

where $\{\varepsilon_t\}$ are independent, identically distributed random variables with $\mathbb{E}(\varepsilon_t) = 0$, $\mathbb{E}(\varepsilon_t^2) = 1$ and $\kappa_4 = \text{cum}_4(\varepsilon_t)$. Under these assumptions we will show in Corollary 3.1, below, that $\hat{c}_T(r) = o_p(1)$

and $\mathcal{T}_m$ converges in distribution to χ_{2m}^2 . Therefore we reject the null of second order stationarity at the $\alpha\%$ significance level if $\mathcal{T}_m > \chi_{2m}^2(1-\alpha)$. We proved the above result under the assumption that the time series is stationary, linear and has absolutely summable covariances. But we believe this result is true even if the process is nonlinear, but stationary or has long memory but is stationary. The proof is beyond the scope of this paper. We need strong mixing condition to prove this general result.

In the case of linearity, (3) has an interesting form. It can be shown that

$$\frac{1}{2\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{f_4(\lambda_1, -\lambda_1 - \omega_r, \lambda_2)}{\sqrt{f(\lambda_1)f(\lambda_1 + \omega_r)f(\lambda_2)f(\lambda_2 + \omega_r)}} d\lambda_1 d\lambda_2 = \kappa_4 \left| \frac{1}{2\pi} \int_0^{2\pi} \exp(i\phi(\omega) - \phi(\omega + \omega_r)) d\omega \right|^2,$$

where

$$\phi(\omega) = \arctan \frac{\Im A(\omega)}{\Re A(\omega)} \text{ and } A(\omega) = \frac{1}{\sqrt{2\pi}} \sum_{j=0}^{\infty} \psi_j \exp(i\omega j).$$

Hence in the case of linearity, the test statistic is equivalent to

$$\mathcal{T}_m = T \sum_{n=1}^m \frac{|\hat{c}_T(r_n)|^2}{1 + \frac{\kappa_4}{2} \left| \frac{1}{2\pi} \int_0^{2\pi} \exp(i\phi(\omega) - \phi(\omega + \frac{2\pi r_n}{T})) d\omega \right|^2}. \quad (5)$$

Moreover, if m is small and small lags are used (ie. $r_n = n$) then the test statistic can be approximated by $\mathcal{T}_m = T \sum_{r=1}^m |\hat{c}_T(r)|^2 / (1 + \kappa_4/2)$.

Remark 2.1 (Estimation of the tri-spectra) *We observe that the test statistic $\mathcal{T}_m$ requires estimates of the parameter*

$$\kappa_r = \frac{1}{2\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{f_4(\lambda_1, -\lambda_1 - \omega_r, -\lambda_2)}{\sqrt{f(\lambda_1)f(\lambda_1 + \omega_r)f(\lambda_2)f(\lambda_2 + \omega_r)}} d\lambda_1 d\lambda_2.$$

Therefore to estimate the above parameter we require estimators of the tri-spectra and spectral density f_4 and f respectively. Brillinger and Rosenblatt (1967) propose a consistent estimator of the tri-spectra $f_4(\cdot)$, which we denote as $\hat{f}_{4,T}(\cdot)$. Therefore an estimator of the above integral is

$$\hat{\kappa}_{r,T} = \frac{1}{2\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{\hat{f}_{4,T}(\lambda_1, -\lambda_1 - \omega_r, -\lambda_2)}{\sqrt{\hat{f}_T(\lambda_1)\hat{f}_T(\lambda_1 + \omega_r)\hat{f}_T(\lambda_2)\hat{f}_T(\lambda_2 + \omega_r)}} d\lambda_1 d\lambda_2,$$

where $\hat{f}_T(\lambda_2)$ is defined in (1). Since $\hat{\kappa}_{r,T}$ is a consistent estimator of κ_r , replacing κ_r in the test statistic with $\hat{\kappa}_{r,T}$, does not alter the asymptotic sampling distribution.

Remark 2.2 (Practical issues) *The asymptotic distribution under the null is derived under the assumptions that the spectral density of the time series $\{X_t\}$ is bounded away from zero. In prac-*

tice, even if this assumption holds, the estimated spectral density $\hat{f}_T(\cdot)$ may be quite close to zero. Therefore, in this case, to prevent falsely rejecting the null, we suggest adding a small ridge to the spectral density estimator $\hat{f}_T(\cdot)$ to bound it away from zero.

2.3 The power of the test

In Section 4 we obtain the asymptotic sampling properties of the test statistic $\mathcal{T}_m$, under the alternative of local stationarity. In order to understand what nonstationary behaviour the test statistic can detect and how to select the lag r in the test statistic, we will now outline some of the results in Section 4. Suppose that $\{X_t\}$ is a nonstationary time series, where in a small neighbourhood of t the observations are close to stationary and has the local spectral density $f(\frac{t}{T}, \omega)$. In Lemma 4.1 we show that $\hat{c}_T(r) \approx B(r)$, where

$$B(r) = \frac{1}{2\pi} \int_0^{2\pi} \int_0^1 \frac{1}{[f(\lambda)f(\lambda + \omega_r)]^{1/2}} f(u, \lambda) \exp(-i\frac{2\pi t}{T}r) du d\lambda, \quad (6)$$

and that $\mathcal{T}_m$ has asymptotically a type of non-central chi squared distribution where the noncentrality parameters are given by $\{B(r_n)\}$. Hence, the test statistic is more likely to reject the null, the further $B(r_n)$, is from from zero. Studying the above we see that if the dynamics change slowly over time, then a small lag r_n , should yield a large $B(r)$. On the other hand, if there is a rapid change in the behaviour, a large r_n , leads to a large $B(r_n)$. Therefore, in this case, by using a large r_n , we are more likely to reject the null.

3 Sampling properties of the test statistic under the null

We now derive the asymptotic distribution under the null of stationarity. We will use the following assumptions.

Assumption 3.1 *Let us suppose that $\{X_t\}$ satisfies (4).*

Let $A(\omega) = (2\pi)^{1/2} \sum_{j=0}^{\infty} \psi_j \exp(ij\omega)$ and define the spectral density $f(\omega) = |A(\omega)|^2$. Assume

- (i) $\sum_{j=0}^{\infty} |j\psi_j| < \infty$ (noting that this implies $\sup_{\omega} |f'(\omega)| < \infty$).*
- (ii) $\mathbb{E}(|\varepsilon_t^{16}|) < \infty$.*
- (iii) $\inf_{\omega} f(\omega) > 0$ and $\inf_{\omega} |\Re A(\omega)|^2 > 0$.*
- (iv) Either (a) $\sum_j |j^2\psi_j| < \infty$ or (b) the derivative of the spectrum $f'(\omega)$ is piecewise montone on the interval $[0, 2\pi]$ (in other words $f'(\cdot)$ can be partitioned into a finite number of intervals which is either nonincreasing or nondecreasing).*

We use Assumption 3.1(i,ii) to show asymptotic normality if $\widehat{c}_T(r)$ (in fact Assumption 3.1(ii) is used to obtain the error when replacing $\widehat{c}_T(r)$, with $\widetilde{c}_T(r)$, defined below). We use Assumption 3.1(iv) to obtain the rate of decay of the Fourier coefficients of the function $\frac{1}{\sqrt{f(\omega)f(\omega+\omega_r)}}$.

To simplify the analysis of the test statistic $\mathcal{T}_m$ we replace the denominator in the covariance $\widehat{c}_T(r)$ with its deterministic limit. To do this, we define the unobserved covariance

$$\widetilde{c}_T(r) = \frac{1}{T} \sum_{k=1}^T \frac{J_T(\omega_k) \overline{J_T(\omega_{k+r})}}{\sqrt{f(\omega_k)f(\omega_{k+r})}}, \quad (7)$$

and obtain the asymptotic distribution of $\widetilde{c}_T(r)$.

In the following lemma we show that the difference between $\sqrt{T}|\widehat{c}_T(r) - \widetilde{c}_T(r)|$ is negligible.

Theorem 3.1 *Suppose Assumption 3.1 is satisfied and let $\widehat{c}_T(r)$ and $\widetilde{c}_T(r)$ be defined as in (2) and (7) respectively. Then we have*

$$\sqrt{T}|\widehat{c}_T(r) - \widetilde{c}_T(r)| = O_p\left((b + \frac{1}{\sqrt{bT}}) + (\frac{1}{bT^{1/2}} + b^2T^{1/2})(\frac{1}{|r|} + \frac{1}{T^{1/2}})\right). \quad (8)$$

PROOF. See Appendix A.2, Lemma A.7, equation (23). $\square$

In the following lemma we derive the asymptotic variance of $\widetilde{c}_T(r)$, and show that $\widetilde{c}_T(r)$ is asymptotically uncorrelated at different lags r , and at the real and imaginary parts.

Lemma 3.1 *Suppose Assumption 3.1 holds. Then we have*

$$\begin{aligned} \text{cov}(\sqrt{T}\Re\widetilde{c}_T(r_1), \sqrt{T}\Re\widetilde{c}_T(r_2)) &= \text{cov}(\sqrt{T}\Im\widetilde{c}_T(r_1), \sqrt{T}\Im\widetilde{c}_T(r_2)) \\ &= \begin{cases} O(\frac{1}{T}) & r_1 \neq r_2 \\ 1 + \frac{\kappa_4}{2} \left| \frac{1}{2\pi} \int_0^{2\pi} \exp(i\phi(\omega) - \phi(\omega + \frac{2\pi r_1}{T})) d\omega \right|^2 + O(\frac{1}{T}) & r_1 = r_2 \end{cases}, \end{aligned}$$

and for all $r_1, r_2 \in \mathbb{Z}$, $\text{cov}(\sqrt{T}\Im\widetilde{c}_T(r_1), \sqrt{T}\Re\widetilde{c}_T(r_2)) = O(\frac{1}{T})$.

PROOF. See Appendix A.3. $\square$

We now show normality of $\widehat{c}_T(r)$, which we use to obtain the distribution of $\mathcal{T}_m$.

Theorem 3.2 *Suppose Assumption 3.1 holds. Then for fixed m we have*

$$\sqrt{T} \left(\frac{1}{1 + \frac{\kappa_4}{2} \varphi(\frac{r_1}{T})} \Re\widehat{c}_T(r_1), \dots, \frac{1}{1 + \frac{\kappa_4}{2} \varphi(\frac{r_m}{T})} \Im\widehat{c}_T(r_m) \right) \xrightarrow{D} \mathcal{N}(0, I_{2m}), \quad (9)$$

as $m(b + \frac{1}{\sqrt{bT}}) + (\frac{1}{bT^{1/2}} + b^2T^{1/2}) \sum_{r=1}^m (\frac{1}{|r_m|} + \frac{1}{T^{1/2}}) \rightarrow 0$ and $T \rightarrow \infty$, where I_{2m} is the identity matrix and $\varphi(x) = \left| \frac{1}{2\pi} \int_0^{2\pi} \exp(i\phi(\omega) - \phi(\omega + x)) d\omega \right|^2$.

PROOF. See Appendix A.4. □

By using the above we are able to obtain the asymptotic distribution of $\mathcal{T}_m$.

Corollary 3.1 *Suppose Assumption 3.1 holds. Then for fixed m we have $\mathcal{T}_m \xrightarrow{D} \chi_{2m}^2$ with $m(b + \frac{1}{\sqrt{bT}}) + (\frac{1}{bT^{1/2}} + b^2T^{1/2}) \sum_{n=1}^m (\frac{1}{|r_n|} + \frac{1}{T^{1/2}}) \rightarrow 0$, as $T \rightarrow \infty$.*

PROOF. The result immediately follows from Theorem 3.2. □

Hence we have shown under the null, that the test statistics has asymptotically a χ^2 distribution.

4 Sampling properties of the test statistic under the alternative of local stationarity

It is useful to investigate the behaviour of the test statistic in the case that the null does not hold. If the covariance structure varies over time, then the limit of $\widehat{c}_T(r)$ will not be zero. This suggests that the test statistic will have a type of non-central χ^2 distribution. However, in the case that time-varying covariance has no structure it is not clear what the limit of $\widehat{c}_T(r)$ will be. For example, consider the simple example of a time-varying AR process, $X_t = a(t)X_{t-1} + \varepsilon_t$, where $\{\varepsilon_t\}$ are iid random variables. Without any structure on the AR coefficient, $a(t)$, it is not clear what the spectral density estimator, $\widehat{f}_T(\cdot)$, defined in (1) should converge to. Hence it is not possible to obtain the limit of $\widehat{c}_T(r)$. On the other hand, let us suppose that $a(t)$, varies slowly over time and $a(t)$ is a sample from a function $a : [0, 1] \rightarrow \mathbb{R}$, that is for some T , $a(t) = a(\frac{t}{T})$, and the time series satisfies $X_{t,T} = a(\frac{t}{T})X_{t-1,T} + \varepsilon_t$, $t = 1, \dots, T$. Now in this set up, as we let $T \rightarrow \infty$, $a(\cdot)$ varies less and $X_{t,T}$ is observed on a finer grid, which in reality can never be realised. Hence, by supposing that $a(\cdot)$ varies slowly over time we have imposed some structure on the time-varying parameter and we are using an infill asymptotic argument (see Robinson (1989)). In this case, we will show, below, that $\widehat{f}_T(\cdot)$ is an estimator of the integrated spectrum, this can also be viewed as the average of local spectrums. The model described above, is an example of a locally stationary linear time series considered in Dahlhaus (1997) and Dahlhaus and Polonik (2006). Therefore, following Dahlhaus and Polonik (2006), we define a locally stationary linear time series as

$$X_{t,T} = \sum_{j=0}^{\infty} \psi_{t,T}(j) \varepsilon_{t-j}, \tag{10}$$

where $\{\varepsilon_t\}$ are iid random variables, $\mathbb{E}(\varepsilon_t) = 0$, $\text{var}(\varepsilon_t) = 1$. Therefore we will consider the behaviour of the test statistic under the alternative of local stationarity.

In order for $\{X_{t,T}\}$ to be a locally stationary time series, we will assume that $\psi_{t,T}(j)$ closely approximates the smooth function $\psi_j(\cdot)$. Hence the time-varying MA parameters $\{\psi_{t,T}(j)\}$ vary slowly over time. It can be shown that in this case, $\{X_{t,T}\}$ is a locally stationary time series because it can locally be approximated by a stationary time series. We will use the following assumptions.

Assumption 4.1 *Let us suppose that $\{X_{t,T}\}$ satisfies (10). Suppose, there exists a sequence of functions $\psi_j(u)$, such that $\psi_j(u)$ is Lipschitz continuous and $|\psi_j(\frac{t}{T}) - \psi_{t,T}(j)| \leq T^{-1}\ell(j)^{-1}$, where $\{\ell(j)^{-1}\}$ is a positive monotonically decreasing function which satisfies $\sum_j |j|^2 \ell(j)^{-1} < \infty$. Let $f(u, \omega) = (2\pi)^{-1} |\sum_{j=0}^{\infty} \psi_j(u) \exp(ij\omega)|^2$ (hence $\sup_{u, \omega} |\frac{\partial^2 f(u, \omega)}{\partial \omega^2}| < \infty$).*

(i) $\sup_u |\psi_j(u)| < \ell(j)^{-1}$ and $\sup_u |\frac{d\psi_j(u)}{du}| < K\ell(j)^{-1}$ (hence $\sup_{u, \omega} |\frac{\partial f(u, \omega)}{\partial u}| < \infty$).

(ii) $\mathbb{E}(|\varepsilon_t^{16}|) < \infty$.

(iii) Define the integrated spectral density $f(\omega) = \int_0^1 f(u, \omega) du$, and assume that $\inf_{\omega} f(\omega) > 0$.

(iv) Either (a) $\sup_u \sum_j |\psi_j''(u)| < \infty$ (hence $\sup_{u, \omega} |\frac{\partial^2 f(u, \omega)}{\partial u^2}| < \infty$) or (b) $A(u, \omega)$ and $\frac{\partial A(u, \omega)}{\partial u}$ are piecewise monotone functions with respect to u .

We will show in Lemma 4.1, below, that in the locally stationary case the spectral density estimator $\widehat{f}_T(\cdot)$ defined in (1) estimates the integrated spectrum $f(\omega)$, where $f(\omega)$ is defined in Assumption 4.1(iii). Roughly speaking, one can consider the integrated spectrum as the average of the locally stationary spectrums.

As in Section 3, it is difficult to directly obtain the distribution of $\widehat{c}_T(r)$. Instead we replace the random denominator with its deterministic limit (that is $J_T(\omega_k)/\sqrt{\widehat{f}_T(\omega_k)}$ with $J_T(\omega_k)/\sqrt{f(\omega_k)}$), and define

$$\widetilde{c}_T(r) = \frac{1}{T} \sum_{k=1}^T \frac{J_T(\omega_k) \overline{J_T(\omega_{k+r})}}{\sqrt{f(\omega_k) f(\omega_{k+r})}}, \quad (11)$$

where $f(\cdot)$ is the integrated spectrum. The following result is the locally stationary analogue of Theorem 3.1.

Theorem 4.1 *Suppose Assumption 3.1 is satisfied, and let $\widehat{c}_T(r)$ and $\widetilde{c}_T(r)$ be defined as in (2) and (11) respectively. Then we have*

$$\sqrt{T} |\widehat{c}_T(r) - \widetilde{c}_T(r)| = O_p \left(\frac{1}{\sqrt{bT}} + \left(\frac{1}{bT^{1/2}} + b^2 T^{1/2} \right) \left(\frac{1}{|r|} + \frac{1}{T^{1/2}} \right) \right).$$

PROOF. In Appendix A.2, Lemma A.7, equation (24). $\square$

From the lemma above we see that in order for the sampling properties of $\sqrt{T}\hat{c}_T(r)$ and $\sqrt{T}\tilde{c}_T(r)$ to coincide, we require that $T^{-1/2} \ll b \ll T^{-1/4}$.

We now obtain the mean and variance of $\tilde{c}_T(r)$ under the alternative hypothesis of local stationarity.

Lemma 4.1 *Suppose Assumption 4.1 are satisfied and let $f(\omega)$ and $f(u, \omega)$ be the integrated and local spectrum (defined in Assumption 4.1) respectively. Then we have*

$$\mathbb{E}(\hat{f}_T(\omega) - f(\omega))^2 = O(b^2 + \frac{1}{bT}), \quad (12)$$

$$\mathbb{E}(\tilde{c}_T(r)) \rightarrow \frac{1}{2\pi} \int_0^{2\pi} \frac{1}{[f(\omega)f(\omega + \omega_r)]^{1/2}} \left(\int_0^1 f(u, \omega) \exp(-2i\pi ru) du \right) d\omega, \quad (13)$$

as $T \rightarrow \infty$, and

$$\begin{aligned} \text{cov}(\Re\sqrt{T}\tilde{c}_T(r_1), \Re\sqrt{T}\tilde{c}_T(r_2)) &\rightarrow \Sigma_{T,r_1,r_2}^{(1,1)} & \text{cov}(\Re\sqrt{T}\tilde{c}_T(r_1), \Im\sqrt{T}\tilde{c}_T(r_2)) &\rightarrow \Sigma_{T,r_1,r_2}^{(1,2)} \\ \text{cov}(\Im\sqrt{T}\tilde{c}_T(r_1), \Im\sqrt{T}\tilde{c}_T(r_2)) &\rightarrow \Sigma_{T,r_1,r_2}^{(2,2)}, \end{aligned} \quad (14)$$

$b \rightarrow 0$, $bT \rightarrow \infty$ as $T \rightarrow \infty$, where

$$\Sigma_{T,r_1,r_2}^{(1,1)} = \frac{1}{4}(\Gamma_{T,r_1,r_2}^{(1)} + \Gamma_{T,r_1,r_2}^{(2)} + \Gamma_{T,r_2,r_1}^{(2)} + \Gamma_{T,r_1,r_2}^{(3)}) + O(\frac{\log T}{T}),$$

$$\Sigma_{T,r_1,r_2}^{(1,2)} = \frac{-i}{4}(\Gamma_{T,r_1,r_2}^{(1)} + \Gamma_{T,r_1,r_2}^{(2)} - \Gamma_{T,r_2,r_1}^{(2)} - \Gamma_{T,r_1,r_2}^{(3)}) + O(\frac{\log T}{T}),$$

$$\Sigma_{T,r_1,r_2}^{(2,2)} = \frac{1}{4}(\Gamma_{T,r_1,r_2}^{(1)} - \Gamma_{T,r_1,r_2}^{(2)} - \Gamma_{T,r_2,r_1}^{(2)} + \Gamma_{T,r_1,r_2}^{(3)}) + O(\frac{\log T}{T}),$$

and $\Gamma_{T,r_2,r_1}^{(i)}$ ($i = 1, 2, 3$) are defined in Lemma A.12 (in Appendix A.3).

PROOF. See Appendix A.3. $\square$

We use the above to obtain the asymptotic distribution of $\mathcal{T}_m$ under the alternative. First we recall that we estimated the standardisation of $\hat{c}_T(r)$, κ_r , in Remark 2.1. It is worth noting that in the case that of local stationarity, $\hat{\kappa}_{r,T}$ is an estimator of

$$\kappa_r = \frac{1}{2\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{f_4(\lambda_1, -\lambda_1 - \omega_r, -\lambda_2)}{\sqrt{f(\lambda_1)f(\lambda_1 + \lambda_2)f(\lambda_2)f(\lambda_2 + \omega_r)}} d\lambda_1 d\lambda_2,$$

where $f(\cdot)$ is the integrated spectral density and $f_4(\lambda_1, \lambda_2, \lambda_3) = \int_0^1 f_4(u, \lambda_1, \lambda_2, \lambda_3) du$, with $f_4(u, \lambda_1, \lambda_2, \lambda_3) = \frac{1}{2\pi} A(u, -\lambda_1 - \lambda_2 - \lambda_3) \prod_{i=1}^3 A(u, \omega_i)$.

Theorem 4.2 *Suppose Assumption 4.1 holds. Let*

$$\Sigma = \begin{pmatrix} \Sigma_T^{(1,1)} & \Sigma_T^{(1,2)} \\ \Sigma_T^{(2,1)} & \Sigma_T^{(2,2)} \end{pmatrix},$$

where $\Sigma_{T,r_1,r_2}^{(1,1)}$, $\Sigma_{T,r_1,r_2}^{(1,2)}$, $\Sigma_{T,r_1,r_2}^{(2,2)}$ are defined in Lemma 4.1 and $\Sigma_{T,r_1,r_2}^{(1,2)} = \overline{\Sigma_{T,r_1,r_2}^{(2,1)}}$.

Furthermore define $\boldsymbol{\mu}' = (\Re B(r_1), \dots, \Re B(r_n), \Im B(r_1), \dots, \Im B(r_n))$, where

$$B(r_n) = \frac{1}{2\pi} \int_0^{2\pi} \frac{1}{[f(\omega)f(\omega + \omega_{r_n})]^{1/2}} \int_0^1 f(u, \omega) \exp(-2i\pi r_n u) du d\omega.$$

Then we have

$$\mathcal{T}_m \xrightarrow{D} \sum_{n=1}^m \frac{(X_n^2 + Y_n^2)}{(1 + \frac{1}{2}\kappa_{r_n})},$$

with $\frac{m}{\sqrt{bT}} + (\frac{1}{bT^{1/2}} + b^2 T^{1/2}) \sum_{n=1}^m (\frac{1}{|r_n|} + \frac{1}{T^{1/2}}) \rightarrow 0$ as $T \rightarrow 0$, where $\mathbf{X}_{2m}$ is a normally distributed random vector with $\mathbf{X}_{2m} = (X_1, \dots, X_m, Y_1, \dots, Y_m)'$ and $\mathbf{X}_{2m} \sim \mathcal{N}(\boldsymbol{\mu}, \Sigma)$. Note the small abuse of notation, when we say $A \xrightarrow{D} B$, we mean that the distribution of random variable A converges to the distribution of random variable B .

Remark 4.1 We observe that if the matrix Σ , define in the theorem above, were the identity matrix, then the limiting distribution of $\mathcal{T}_m$, is a non-central χ_{2m}^2 where the noncentrality parameter is determined by the limit of $\widehat{c}_T(r_n)$ (for $n = 1, \dots, m$). Hence the power of the test depends on the deviation of

$\frac{1}{2\pi} \int_0^{2\pi} \frac{1}{[f(\omega)f(\omega + \omega_{r_n})]^{1/2}} \int_0^1 f(u, \omega) \exp(-2i\pi r_n u) du d\omega$ from zero, for each of the lags r_n . We see that term depends on the Fourier coefficient $a(r_n; \omega) := \int_0^1 f(u, \omega) \exp(-2i\pi r_n u) du d\omega$ and the magnitude of $a(r_n; \omega)$ depends on whether the frequency of the nonstationary variation matches r_n .

However, in the case that $X_{t,T}$ is a second order nonstationary time series, Σ will not be a diagonal time series, because there is correlation between the real and imaginary parts of $\widetilde{c}_T(r)$ and also correlation at different lags r . Thus the limiting distribution of $\mathcal{T}_m$ will not be a classical non-central χ_{2m}^2 , due to the correlations in Σ . However, the conclusions discussed above still hold, namely the power of the test is determined, mainly, by the magnitude of mean vector $\boldsymbol{\mu}$.

5 Simulations

We now consider a simulation study. We compare the results of the test statistic for both stationary and nonstationary time series. In each case, we replicate the time series 1000 times, and for each replication we do the test. We do the test for sample sizes $T = 256$ and $T = 512$. We do the test for $m = 1, 5$ and 10 . The percentage of time the test statistic exceeds $\chi_{2m}^2(0.05)$, that is $\mathcal{T}_m > \chi_{2m}^2(0.05)$ is given in the tables, we also give plots of the empirical density of the test statistic.

5.1 Stationary time series

We first investigate the behaviour of the test statistic under the null hypothesis of stationarity.

- (i) Model 1: $X_t = 0.8X_{t-1} + \varepsilon_t$, where $\{\varepsilon_t\}$ are iid Gaussian random variables. We do the test for consecutive lags $r = 1, \dots, m$, the results can be found in the table below. A plot of the estimated finite sample density of the test statistic is given in Figure 1.

$T = 256$	$m = 1$	$m = 5$	$m = 10$	$T = 512$	$m = 1$	$m = 5$	$m = 10$
% reject	6	5	8	% reject	5.3	6.4	6.5

- (ii) Model 2: $X_t - X_{t-1} - 0.7X_{t-2} = \varepsilon_t + 0.3\varepsilon_{t-1} + 2\varepsilon_{t-3}$, $\{\varepsilon_t\}$ are Gaussian. We do the test for consecutive lags $r = 1, \dots, m$, the results can be found in the table below. A plot of the estimated finite sample density of the test statistic $\mathcal{T}_{10}$ is given in Figure 1.

$T = 256$	$m = 1$	$m = 5$	$m = 10$	$T = 512$	$m = 1$	$m = 5$	$m = 10$
% reject	4.9	5.9	6.3	% reject	8.33	4.67	3.33

We observe that under the null of stationarity, the percentage rejects, in the tables, and the plots of the empirical density in Figure 1 suggest that the χ^2 -distribution approximates well the distribution of the test statistic $\mathcal{T}_m$.

5.2 Nonstationary time series

We now investigate the performance of the test statistic under different types of nonstationary behaviour.

- (i) Model 3: In this model there is a change point occurring in the later part of the time series: $X_t = 1.5X_{t-1} - 0.75X_{t-1} + \varepsilon_t$ for $t = 1, \dots, 0.75T$ and $X_t = 0.8X_{t-1} + \varepsilon_t$ for $t = (0.75T + 1), \dots, T$. We do the test for consecutive lags $r = 1, \dots, m$, the results can be found in the table below. A plot of the estimated finite sample density of the test statistic $\mathcal{T}_{10}$ is given in Figure 2.

$T = 256$	m=1	m=5	m=10	$T = 512$	m=1	m=5	m=10
% reject	100	100	100	% reject	100	100	100

- (ii) Model 4: In this model the variance of the innovation changes smoothly over time: $X_t = 0.8X_{t-1} + \sigma_t \varepsilon_t$, where $\sigma_t = (\frac{1}{2} + \sin(\frac{2t\pi}{512}) + 0.3 \cos(\frac{2t\pi}{512}))$, where $\{\varepsilon_t\}$ are Gaussian. We do the test for consecutive lags $r = 1, \dots, m$, the results can be found in the table below. A plot of the estimated finite sample density of the test statistic $\mathcal{T}_{10}$ is given in Figure 2.

T=256	m=1	m=5	m=10	T=512	m=1	m=5	m=10
% reject	6.6	16.9	26.6	% reject	99.9	98	94.6

We mention, that for $1 \leq t \leq 256$, function σ_t defined above, does not vary much, which explains why the rejection rate for $T = 256$ is relatively low.

- (iii) Model 5: In this model there is a change point, but the change is quite small: $X_t = 0.8X_{t-1} + \varepsilon_t$ for $t = 1, \dots, 0.5T$ and $X_t = 0.6X_{t-1} + \varepsilon_t$ for $t = (0.5T + 1), \dots, T$, where $\{\varepsilon_t\}$ are Gaussian. We do the test for consecutive lags $r = 1, \dots, m$, the results can be found in the table below.

T=256	m=1	m=5	m=10	T=512	m=1	m=5	m=10
% reject	52	35.6	25.2	% reject	82	66	52

- (iv) Model 6: In this model, the time series is independent with time-varying variance. Define the piecewise varying function $\sigma : [0, 1] \rightarrow \mathbb{R}$

$$\sigma(u) = \begin{cases} 1 & \text{for } u \in \{[\frac{5}{20}, \frac{6}{20}), [\frac{14}{20}, \frac{15}{20}), [\frac{16}{20}, \frac{17}{20}), [\frac{18}{20}, \frac{19}{20})\} \\ 2 & \text{for } u \in \{[\frac{8}{20}, \frac{12}{20}), [\frac{13}{20}, \frac{14}{20}), [\frac{19}{20}, 1]\} \\ 3 & \text{for } u \in \{[0, \frac{5}{20}), [\frac{6}{20}, \frac{7}{20}), [\frac{12}{20}, \frac{13}{20}), [\frac{15}{20}, \frac{16}{20}), [\frac{17}{20}, \frac{18}{20})\} \end{cases}$$

and the time series $X_{t,T} = \sigma(\frac{t}{T})\varepsilon_t$, where $\{\varepsilon_t\}$ are iid Gaussian random variables. A plot of a realisation of the time series and the function $\sigma(\cdot)$ is given in Figure 4. We do the test for consecutive lags $r = 1, \dots, m$, the results can be found in the table below.

T=256	m=1	m=5	m=10	T=512	m=1	m=5	m=10
% reject	39	59	79	% reject	62	85	99

We observe that the rejection rate increases as the number of lags used in the test grows. We now investigate why. In Figure 5, we plot the rejection rate of $\mathcal{T}_1$ (hence one lag) at lags $r = 1, \dots, 120$, we do this for both sample sizes $T = 256$ and $T = 512$ and we also plot the absolute values of the Fourier coefficients of the function $\sigma(\cdot)$ for $r = 1, \dots, 120$ (ie. $\{|a_r|\}$, where $\sigma(u) = \sum_r a_r \exp(-ir\omega)$, which are estimated with $\hat{a}_{r,T} = \frac{1}{T} \sum_{t=1}^{512} \sigma(\frac{t}{512}) \exp(\frac{-i2\pi r t}{512})$). We observe that with one lag (in the test statistic) the rejection rate is greatest at the frequencies

r that the Fourier coefficients are largest. This illustrates well the theory of the test statistic under the alternative. More precisely, for this model, the time-varying spectral density is approximately $f(u, \omega) = \sigma(u)^2$, and the noncentrality parameter is largest when the Fourier coefficient $\int_0^1 f(u, \omega) \exp(-2i\pi ru) du = \int_0^1 \sigma(u)^2 \exp(-2i\pi ru) du$ is largest.

We observe that for various types of nonstationary behaviour the test has good power. Moreover, we observe that for many types of nonstationarity, by using a few small number of lags r , we are still able to reject the null hypothesis.

6 Real data analysis

To illustrate the test for second order stationarity we consider two real data examples. For both data sets we will use the test statistic $\mathcal{T}_4 = T \sum_{r=1}^4 |\hat{c}_T(r)|^2$. We choice $m = 4$, because the simulations in the previous section show that most nonstationary behaviour appears to be captured in the first four lags. We recall that under the null $\mathcal{T}_4$ asymptotically has a chi squared distribution with eight degrees of freedom.

We first test for second order stationarity of the monthly southern oscillation index time series observed between January 1950 to December 1987 ($T = 453$). The data can be found at <http://www.stat.pitt.edu/stoffer/tsa2/>, a plot is given in Figure 6. The test statistic gives the value $\mathcal{T}_4 = 2.66$, which corresponds to a p-value of 0.95, hence there is no evidence to reject the null of second order stationarity.

In our second data example we consider the daily British pound/US dollar exchange rate data observed between January 2000 to October 2009. This data was obtained from <http://federalreserve.gov/re>. In order to ensure the existence of moments we tranformed the data and considered the square root of the absolute log differences, that is $X_t = |\log Y_t^2 - \log Y_{t-2}^2|^{1/2}$, where Y_t is the exchange rate at time t . A plot of the transformed data is given in Figure 7. The test statistic based on the entire data set gave the value $\mathcal{T}_4 = 99.4$, which corresponds to the p-value $p \approx 0$. Thus suggests there is evidence to reject the null of second order stationarity. To locate the regions of nonstationarity the data is partioned into segments of half length, quarter length and eighth length and the test was performed on each of these segments. The results are given in Table 1. Studying Table 1 and the p-values, there is evidence to suggest that for most periods there is no evidence to reject the null of stationarity. However, over the blocks June 2002 - November 2004, and August 2008 - October 2009, the data seems to be second order nonstationary. This information can be used to fit a model with time-varying parameters to the data.

Jan'00	Mar'01	Jun'02	Sep'03	Nov'04	Feb'06	May'07	Aug'08
$T = 99.4 \ p = 0.000$							
$T = 29.5 \ p = 0.000$				$T = 78.43 \ p = 0.000$			
$T = 20.0 \ p = 0.010$		$T = 23.9 \ p = 0.002$		$T = 5.1 \ p = 0.752$		$T = 51.4 \ p = 0.000$	
$T = 7.2$ $p = 0.520$	$T = 15.5$ $p = 0.055$	$T = 19.4$ $p = 0.013$	$T = 18.2$ $p = 0.020$	$T = 5.5$ $p = 0.702$	$T = 12.0$ $p = 0.151$	$T = 12.1$ $p = 0.145$	$T = 17.9$ $p = 0.022$

Table 1: Test Statistics and p-value

7 Conclusions

In this article we have considered a test for second order stationarity. The test is based on the property that the DFT of a second order stationary time series is close to uncorrelated. The sampling properties of the test statistic under the null are derived under the assumption that the time series satisfies a short memory, $MA(\infty)$ representation. However, empirical evidence suggest that similar sampling properties also hold in the case of both stationary long memory and nonlinear time series too. For this general case, it may be possible to use some of the theory developed in Kokoszka and Mikosch (2000), however, this is beyond the scope of the current paper and is future work.

Acknowledgements

The authors are grateful to Professor Manfred Deistler for several interesting discussions. This work has been partially supported by the NSF grant DMS-0806096.





Figure 1: The estimate density of the test statistic $\mathcal{T}_{10}$ for Left: Stationary Model 1 and Right: stationary Model 2 ($T = 512$)





Figure 2: Estimate density of test statistic for Left: Nonstationary Model 3 and Right: Nonstationary Model 4 (right). ($T = 512$)





Figure 3: Left: Stationary realisation Model 1. Right: Nonstationary realisation Model 4.




Figure 4: Top: A realisation from nonstationary Model 6. Lower: The time varying function $\sigma(\cdot)$




Figure 5: Top: The x-axis is the lag used in the test statistic $r = 1, \dots, 120$ and the y -axis is the corresponding rejection rate using the test statistic $\mathcal{T}_1 > \chi_2^2(0.05)$ for $T = 256$ and $T = 512$. Lower: Absolute values of the Fourier coefficients of $\sigma(\cdot)$.




Figure 6: Monthly southern oscillation index time series between January 1950 to December 1987




Figure 7: Daily British pound/US dollar exchange rate data observed between January 2000 to October 2009

A Appendix

In this appendix we prove the results from the main section.

For short hand, when it is clear that T plays a role, we use the notation $J_k := J_T(\omega_k)$, $\bar{J}_k = J_T(-\omega_k)$, $\hat{f}_k := \hat{f}_T(\omega_k)$ and $f_k = f(\omega_k)$.

A.1 Some results on DFTs and Fourier coefficients

In the sections below, under various assumptions of the dependence of $\{X_t\}$, we will show asymptotic normality and obtain the mean and variance of $\tilde{c}_T(r)$. In the case that $\{X_t\}$ is a short memory, stationary time series, then it is relatively straightforward to evaluate the variance of $\tilde{c}_T(r)$, since $\{J_T(\omega_k)\overline{J_T(\omega_{k+r})}\}$ are close to uncorrelated random variables. However, in the nonstationary case this no longer holds and we have to use some results in Fourier analysis to derive $\text{var}(\tilde{c}_T(r))$. To do

this we start by studying the general random variable

$$H_T = \frac{1}{T} \sum_{k=1}^T H(\omega_k) J_T(\omega_k) \overline{J_T(\omega_{k+r})},$$

where $J_T(\omega_k) = \frac{1}{\sqrt{2\pi T}} \sum_{t=1}^T X_t \exp(\frac{2\pi i t k}{T})$. We will show that under certain conditions on $H(\cdot)$, H_T can be written as the weighted average of X_t . Expanding $J_T(\omega_k) \overline{J_T(\omega_k)}$ we see that H_T can be written as

$$H_T = \frac{1}{T} \sum_{t,\tau} X_t X_\tau \exp(-i\omega_r \tau) \left(\frac{1}{T} \sum_{k=1}^T H(\omega_k) \exp(i\omega_k(t-\tau)) \right).$$

Without any smoothness assumptions on $H(\omega_k)$, it is not clear whether the inner sum of the above converges to zero as $|t-\tau| \rightarrow \infty$, and if the variance of H_T converges to zero. However, let us suppose that $\sup_\omega |H'(\omega)| < \infty$. In this case, the DFT of $H(\omega)$, $\frac{1}{T} \sum_{k=1}^T H(\omega_k) \exp(i\omega_k(t-\tau))$, is an approximation of the Fourier coefficient $h(t-\tau) = \int H(\omega) \exp(i(t-\tau)\omega) d\omega$ (the error in this approximation is discussed below). Noting that the Fourier coefficients $h(k) \rightarrow 0$ as $k \rightarrow \infty$, we have

$$H_T \approx \frac{1}{T} \sum_{t=1}^T X_t \sum_{\tau} h(t-\tau) X_\tau \exp(-i\omega_r \tau) := \frac{1}{T} \sum_{t=1}^T X_t Y_t^{(r)}.$$

Now under relatively weak conditions on the Fourier coefficients, $\{h(k)\}$, $Y_t^{(r)}$ is almost surely finite (and second order stationary if $\{X_t\}$ were stationary). Hence H_T can be considered a weighted average of $\{X_t\}$, where the weights in this case are random but almost surely finite. We now justify some of the approximations discussed above and state some well know results in Fourier analysis. An interesting overview of results in Fourier analysis is given in Briggs and Henson (1997).

The following theorem is well known, see for example, Briggs and Henson (1997), Theorem 6.2, for the proof.

Theorem A.1 *Suppose that $g[0, \Omega] \rightarrow \mathbb{R}$ is a periodic function with period Ω . We shall assume that either (a) $\sup_x |g''(x)| < \infty$ or (b) $\sup_x |g'(x)| < \infty$ and $g'(\cdot)$ is piecewise monotone function. Let*

$$a(s) = \frac{1}{\Omega} \int_0^\Omega g(x) \exp(isx) dx \quad \text{and} \quad a_T(s) = \frac{1}{T} \sum_{k=1}^T g\left(\frac{\Omega k}{T}\right) \exp(i \frac{\Omega k}{T} s).$$

Therefore for all s , we have in case (a) $|a(s)| \leq C \sup_x |g''(x)| s^{-2}$ and in case (b) $|a(s)| \leq C \sup_x |g'(x)| s^{-2}$, where C is constant independent of s and $g(\cdot)$.

Moreover $\sup_{1 \leq s \leq T} |a(s) - a_T(s)| \leq CT^{-2}$.

We now apply the above result to our setup. We will use Lemma A.1, below, to prove the asymptotic normality result in Section A.4.

Lemma A.1 *Suppose Assumption 3.1 or Assumption 4.1 is satisfied. And let $f(\omega)$ be the spectral density of the stationary linear time series or the integrated spectral density of the locally stationary time series. Let*

$$G_{T,\omega_r}(s) = \frac{1}{T} \sum_{k=1}^T \frac{1}{(f(\omega_k)f(\omega_k + \omega_r))^{1/2}} \exp(is\omega_k) \quad (15)$$

$$\text{and } G_{\omega_r}(s) = \frac{1}{2\pi} \int_0^{2\pi} \frac{1}{(f(\omega)f(\omega + \omega_r))^{1/2}} \exp(is\omega) d\omega. \quad (16)$$

Under the stated assumptions we have either $(f(\omega)f(\omega + \omega_r))^{-1/2}$ has a bounded second derivative (under Assumption 3.1(iv-a) or Assumption 4.1) or that $(f(\omega)f(\omega + \omega_r))^{-1/2}$ has a bounded first derivative and is piecewise monotone (under Assumption 3.1(iv-b)). Therefore, $\sup_{\omega_r} \sum_s |G_{\omega_r}(s)| < \infty$ and $\sup_{\omega_r} \sum_{s=1}^T |G_{T,\omega_r}(s)| < \infty$.

PROOF. The above is a straightforward application of Theorem A.1. $\square$

We will use the result below in Sections A.2 and A.3.

Lemma A.2 *Suppose Assumption 4.1 is satisfied. Define the n th order cumulant spectra as*

$$f_n(u, \omega_1, \dots, \omega_{n-1}) = \frac{1}{(2\pi)^{(n/2)-1}} \left\{ \prod_{j=1}^{n-1} A(u, \omega_j) \right\} A(u, -\sum_{j=1}^{n-1} \omega_j),$$

and the Fourier transform

$$F_n(k; \omega_1, \dots, \omega_{n-1}) = \int_0^1 f_n(u, \omega_1, \dots, \omega_{n-1}) \exp(i2\pi ku) du. \quad (17)$$

(i) *If Assumption 4.1(iv)(a) holds, then $\sup_{u, \omega_1, \dots, \omega_n} \left| \frac{\partial^2 f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u^2} \right| < \infty$ and*

$$\sup_{\omega_1, \dots, \omega_{n-1}} |F_n(k; \omega_1, \dots, \omega_{n-1})| \leq C \sup_{u, \omega_1, \dots, \omega_n} \left| \frac{\partial^2 f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u^2} \right| \frac{1}{|k|^2}. \quad (18)$$

(ii) *If Assumption 4.1(iv)(b) holds, then $\sup_{u, \omega_1, \dots, \omega_n} \left| \frac{\partial f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u} \right| < \infty$, $\frac{\partial f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u}$ is a piecewise monotone function in u and*

$$\sup_{\omega_1, \dots, \omega_n} |F_n(k; \omega_1, \dots, \omega_{n-1})| \leq C \sup_{u, \omega_1, \dots, \omega_n} \left| \frac{\partial f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u} \right| \frac{1}{|k|^2}. \quad (19)$$

We note that the constant C is independent of the function $f_n(\cdot)$ and k .

PROOF. To ease notation we only prove (ii), the proof of (i) is similar. We note that

$$\begin{aligned} (2\pi)^{(n/2)-1} \frac{df_n(u, \omega_1, \dots, \omega_{n-1})}{du} &= A(u, -\sum_{j=1}^{n-1} \omega_j) \sum_{r=1}^{n-1} \frac{dA(u, \omega_r)}{du} \prod_{j \neq r} A(u, \omega_j) + \\ &\quad \frac{\partial A(u, -\sum_{j=1}^{n-1} \omega_j)}{\partial u} \prod_{j=1}^{n-1} A(u, \omega_j). \end{aligned}$$

Now under Assumption 4.1, $\sup_{u, \omega} |A(u, \omega)|$ and $\sup_{u, \omega} |\frac{\partial A(u, \omega)}{\partial u}|$ are bounded function, hence we see from the above that $\sup_{u, \omega} |\frac{\partial f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u}|$ is bounded. Moreover, by using Theorem A.1 we have (18). The proof of (ii) is similar, and we omit the details. $\square$

We observe that in the stationary case $A(u, \omega) \equiv A(\omega)$, then $F_n(k; \omega_1, \dots, \omega_{n-1}) = 0$ for $k \neq 0$.

In the following lemma we consider the error in approximation of the DFT with the Fourier coefficient.

Lemma A.3 *Suppose Assumption 4.1 is satisfied. Let $F_n(k; \omega_1, \dots, \omega_{n-1})$ be defined as in (17) and let*

$$F_{n,T}(s; \omega_1, \dots, \omega_n) = \frac{1}{T} \sum_{t=1}^T f_n\left(\frac{t}{T}, \omega_1, \dots, \omega_{n-1}\right) \exp(i2s\pi t/T). \quad (20)$$

Then under Assumption 4.1(v)(a) we have

$$\sup_{\omega_1, \dots, \omega_{n-1}} |F_{n,T}(s; \omega_1, \dots, \omega_n) - F_n(s; \omega_1, \dots, \omega_{n-1})| \leq C \sup_{u, \omega_1, \dots, \omega_n} \left| \frac{\partial^2 f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u^2} \right| \frac{1}{T^2},$$

and under Assumption 4.1(v)(b) we have

$$\sup_{\omega_1, \dots, \omega_{n-1}} |F_{n,T}(s; \omega_1, \dots, \omega_n) - F_n(s; \omega_1, \dots, \omega_{n-1})| \leq C \sup_{u, \omega_1, \dots, \omega_n} \left| \frac{\partial f_n(u, \omega_1, \dots, \omega_{n-1})}{\partial u} \right| \frac{1}{T^2},$$

where C is a constant independent of $f_n(\cdot)$.

PROOF. The proof follows immediately from Theorem A.1 and Lemma A.2. $\square$

A.2 Proof of Theorems 3.1 and 4.1

The follow result is due to Paparoditis (2009), Lemma 6.2, and is a generalisation of Brillinger (1981), Theorem 4.3.2, for locally stationary time series.

Lemma A.4 (Paparoditis (2009), Lemma 6.2) *Suppose that Assumption 4.1 holds and let $f_n(\cdot)$ be defined as in (17). Then for $\omega_1, \dots, \omega_n \in [0, 2\pi]$ we have*

$$\text{cum}(J_T(\omega_1), \dots, J_T(\omega_n)) = \frac{(2\pi)^{(n/2)-1}}{T^{n/2}} \sum_{t=1}^T f_n\left(\frac{t}{T}, \omega_1, \dots, \omega_{n-1}\right) \exp(it \sum_{j=1}^n \omega_j) + O\left(\frac{(\log T)^{n-1}}{T^{n/2}}\right).$$

Now the following corollary immediately follows from Lemmas A.3 and A.4.

Corollary A.1 *Suppose that Assumption 4.1 holds, and let $F_n(\cdot)$ be defined as in (17). Then we have*

$$\text{cum}(J_T(\omega_{j_1}), \dots, J_T(\omega_{j_n})) = \frac{(2\pi)^{(n/2)-1}}{T^{(n/2)-1}} F_n(j_1 + \dots + j_n; \omega_{j_1}, \dots, \omega_{j_{n-1}}) + O\left(\frac{(\log T)^{n-1}}{T^{n/2}} + \frac{1}{T^2}\right)$$

and

$$|\text{cum}(J_T(\omega_{j_1}), \dots, J_T(\omega_{j_n}))| \leq C \frac{1}{T^{(n/2)-1} |j_1 + \dots + j_n|} + \frac{C(\log T)^{n-1}}{T^{n/2}} + \frac{C}{T^2},$$

where $\omega_{j_r} = 2\pi j_r/T$, $-T \leq j_r \leq T$ and C is constant independent of ω .

The following well known result represents moments in terms of cumulants.

Lemma A.5 *Let us suppose that $\sup_t \mathbb{E}(|X_t|^n) < \infty$. Then we have*

$$\mathbb{E}(X_{t_1}, \dots, X_{t_n}) = \sum_{\pi} \prod_{B \in \pi} \text{cum}(X_i; i \in B), \quad (21)$$

where π is a partition of $\{t_1, t_2, \dots, t_n\}$ and the sum $\sum_{\pi}$ is done over all partitions of $\{t_1, t_2, \dots, t_n\}$.

We use the above lemmas below.

Lemma A.6 *Suppose either Assumption 3.1 or Assumption 4.1 holds. Let $f(\cdot)$ be the integrated spectral density (or the true spectral density in the case of stationarity). Then we have*

(i)

$$\mathbb{E}\left(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} \left\{ \hat{f}_{k_1} \hat{f}_{k_1+r} - \mathbb{E}(\hat{f}_{k_1} \hat{f}_{k_1+r}) \right\} \left\{ \hat{f}_{k_2} \hat{f}_{k_2+r} - \mathbb{E}(\hat{f}_{k_2} \hat{f}_{k_2+r}) \right\}\right) = \frac{C}{bT} \left(\frac{1}{|k_1 - k_2|^2} + \frac{\log T}{T} \right),$$

(ii)

$$\mathbb{E}\left\{ \hat{f}_k \hat{f}_{k+r} - \mathbb{E}(\hat{f}_k \hat{f}_{k+r}) \right\}^4 \leq \frac{C}{(bT)^2}$$

- (iii) Suppose Assumption 3.1(i) holds, then we have $\mathbb{E}\{\hat{f}_k \hat{f}_{k+r}\} - f_k f_{k+r} = O(b + \frac{1}{bT})$. Suppose Assumption 3.1(iv-a) or Assumption 4.1 holds, then we have $\mathbb{E}\{\hat{f}_k \hat{f}_{k+r}\} - f_k f_{k+r} = O(b^2 + \frac{1}{bT})$.
- (iv) Suppose Assumption 4.1 holds, then we have

$$\begin{aligned} \mathbb{E}(J_{s_1} J_{s_2} J_{s_3} J_{s_4}) &\leq C\left(\frac{1}{|s_1 + s_2|^2} + \delta_T\right)\left(\frac{1}{|s_3 + s_4|^2} + \delta_T\right) + C\left(\frac{1}{|s_1 + s_3|^2} + \delta_T\right)\left(\frac{1}{|s_2 + s_4|^2} + \delta_T\right) \\ &\quad + C\left(\frac{1}{|s_1 + s_4|^2} + \delta_T\right)\left(\frac{1}{|s_2 + s_3|^2} + \delta_T\right) \\ &\quad + \frac{C}{T} \frac{1}{|s_1 + s_2 + s_3 + s_4|^2} + O\left(\frac{(\log T)^3}{T^2} + \frac{1}{T^2}\right), \end{aligned}$$

where $\delta_T = O(\frac{\log T}{T} + \frac{1}{T^2})$.

PROOF. To simplify notation in the proof we let $w_j = \frac{1}{bT} K(\frac{\omega_j}{b})$. By expanding the expectation in (i) we have

$$\begin{aligned} &\mathbb{E}\left(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} \{\hat{f}_{k_1} \hat{f}_{k_1+r} - \mathbb{E}(\hat{f}_{k_1} \hat{f}_{k_1+r})\} \{\hat{f}_{k_2} \hat{f}_{k_2+r} - \mathbb{E}(\hat{f}_{k_2} \hat{f}_{k_2+r})\}\right) \\ &= \sum_{j_1, j_2, j_3, j_4} w_{j_1} w_{j_2} w_{j_3} w_{j_4} \\ &\quad \left\{ \mathbb{E}(J_{k_1-j_1} \bar{J}_{k_1-j_1} J_{k_1+r-j_2} \bar{J}_{k_1+r-j_2} J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} J_{k_2-j_3} \bar{J}_{k_2-j_3} J_{k_2+r-j_4} \bar{J}_{k_2+r-j_4}) \right. \\ &\quad - \mathbb{E}(J_{k_1-j_1} \bar{J}_{k_1-j_1} J_{k_1+r-j_2} \bar{J}_{k_1+r-j_2}) \mathbb{E}(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} J_{k_2-j_3} \bar{J}_{k_2-j_3} J_{k_2+r-j_4} \bar{J}_{k_2+r-j_4}) \\ &\quad - \mathbb{E}(J_{k_2-j_3} \bar{J}_{k_2-j_3} J_{k_2+r-j_4} \bar{J}_{k_2+r-j_4}) \mathbb{E}(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} J_{k_1-j_1} \bar{J}_{k_1-j_1} J_{k_1+r-j_2} \bar{J}_{k_1+r-j_2}) \\ &\quad \left. + \mathbb{E}(J_{k_1-j_3} \bar{J}_{k_1-j_3} J_{k_1+r-j_4} \bar{J}_{k_1+r-j_4}) \mathbb{E}(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r}) \mathbb{E}(J_{k_2-j_3} \bar{J}_{k_2-j_3} J_{k_2+r-j_4} \bar{J}_{k_2+r-j_4}) \right\}. \quad (22) \end{aligned}$$

To prove the result we first represent the above moments in terms of cumulants using Lemma A.5. We observe that many of the terms will cancel, however those that do remain will involve at least one cumulant which has elements belong to the set $\{J_{k_1-j_1}, \bar{J}_{k_1-j_1}, J_{k_1+r-j_2}, \bar{J}_{k_1+r-j_2}\}$ and the set $\{J_{k_2-j_3}, \bar{J}_{k_2-j_3}, J_{k_2+r-j_4}, \bar{J}_{k_2+r-j_4}\}$, since these can only arise the cumulant expansion of $\mathbb{E}(J_{k_1-j_1} \bar{J}_{k_1-j_1} J_{k_1+r-j_2} \bar{J}_{k_1+r-j_2} J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} J_{k_2-j_3} \bar{J}_{k_2-j_3} J_{k_2+r-j_4} \bar{J}_{k_2+r-j_4})$. Now by a careful analysis of all cumulants involving elements from both these two sets we observe that the largest cumulant terms are $\text{cum}(J_{k_1-j_1}, J_{k_2-j_3})$ and $\text{cum}(\bar{J}_{k_1-j_1}, \bar{J}_{k_2-j_3})$ (the rest are of a lower order). Therefore

recalling that $\sum_{j_1, j_2, j_3, j_4} w_{j_1} w_{j_2} w_{j_3} w_{j_4} = \sum_{j_1, j_2, j_3, j_4=1}^{bT} \frac{1}{(bT)^4} \prod_j K(\frac{\omega_j}{b})$ and using Corollary A.1 gives

$$\begin{aligned} & \mathbb{E} \left(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r} \{ \hat{f}_{k_1} \hat{f}_{k_1+r} - \mathbb{E}(\hat{f}_{k_1} \hat{f}_{k_1+r}) \} \{ \hat{f}_{k_2} \hat{f}_{k_2+r} - \mathbb{E}(\hat{f}_{k_2} \hat{f}_{k_2+r}) \} \right) \\ & \leq \sum_{j_1, j_2, j_3, j_4=1}^{bT} \frac{1}{(bT)^4} \prod_{j_i} K(\frac{\omega_{j_i}}{b}) \left(\frac{1}{|k_1 + k_2 - j_1 - j_3|^2} + \frac{\log T}{T} \right)^2 \\ & \leq \frac{C}{bT} \left(\frac{1}{|k_1 - k_2|^2} + \frac{\log T}{T} \right), \end{aligned}$$

where C is a finite constant independent of k_1 and k_2 .

The proof of (ii) is similar to the proof of (i), hence we omit the details. We note that if we were to show asymptotic normality of $\hat{f}_k \hat{f}_{k+r}$, then (ii) would immediately follow from this.

We now prove (iii). By definition of $\hat{f}_k \hat{f}_{k+r}$, using Lemmas A.4 and A.1, under Assumption 3.1(i) we have

$$\begin{aligned} \mathbb{E}\{\hat{f}_k \hat{f}_{k+r}\} - f_k f_{k+r} &= \sum_{j_1, j_2} \frac{1}{(bT)^2} K(\frac{w_{j_1}}{b}) K(\frac{w_{j_2}}{b}) \mathbb{E}\{J_{k-j_1} \bar{J}_{k-j_1} J_{k+r-j_2} \bar{J}_{k+r-j_2}\} - f(\omega_k) f(\omega_{k+r}) \\ &= \sum_{j_1} \frac{1}{bT} K(\frac{w_{j_1}}{b}) f_2(\omega_{k-j_1}) \sum_{j_2} \frac{1}{bT} K(\frac{w_{j_2}}{b}) f_2(\omega_{k+r-j_1}) - f(\omega_k) f(\omega_{k+r}) + O(\frac{1}{bT}) \\ &= O(b + \frac{1}{bT}). \end{aligned}$$

Using a similar proof we can show that under Assumption 3.1(iv-a) or Assumption 4.1 we have $\mathbb{E}\{\hat{f}_k \hat{f}_{k+r}\} - f_k f_{k+r} = O(b^2 + \frac{1}{bT})$. Thus proving (iii).

The proof of (iv) uses Lemma A.4 and Corollary A.1 and is straightforward, hence we omit the details. $\square$

In the lemma below we prove Theorems 3.1 and 4.1.

Lemma A.7 *Suppose Assumption 3.1 holds. Then we have*

$$\sqrt{T} |\hat{c}_T(r) - \tilde{c}_T(r)| = O \left(\frac{1}{\sqrt{bT}} + (b + \frac{1}{bT}) + (\frac{1}{bT^{1/2}} + b^2 T^{1/2}) (\frac{1}{|r|} + \frac{1}{T^{1/2}}) \right). \quad (23)$$

Suppose Assumption 4.1 holds. Then we have

$$\sqrt{T} |\hat{c}_T(r) - \tilde{c}_T(r)| = O \left(\frac{1}{\sqrt{bT}} + (\frac{1}{bT^{1/2}} + b^2 T^{1/2}) (\frac{1}{|r|} + \frac{1}{T^{1/2}}) \right). \quad (24)$$

PROOF. The proofs of (23) and (24) are very similar. Most of the time we will be obtaining the bounds under Assumption 4.1, however in a few places the bounds under Assumption 3.1 can be

better than those under Assumption 4.1. In this case we will obtain the bounds under each of the Assumptions (separately).

To prove both (23) and (24) we first note that by the mean value theorem evaluated to the second order we have $x^{-1/2} - y^{-1/2} = (-1/2)x^{-3/2}(x - y) + (1/2)(-1/2)(-3/2)x_y^{-5/2}(x - y)^2$, where x_y lies between x and y . Applying this to the difference $\widehat{c}_T(r) - \widetilde{c}_T(r)$ we have the expansion

$$\sqrt{T}|\widehat{c}_T(r) - \widetilde{c}_T(r)| \leq \frac{1}{2}I + \frac{3}{8}II,$$

where

$$I = \frac{1}{\sqrt{T}} \sum_k \frac{J_k \bar{J}_{k+r}}{(f_k f_{k+r})^{3/2}} \{ \hat{f}_k \hat{f}_{k+r} - f_k f_{k+r} \} \text{ and } II = \frac{1}{\sqrt{T}} \sum_k \frac{J_k \bar{J}_{k+r}}{(f_k f_{k+r})^{5/2}} \{ \hat{f}_k \hat{f}_{k+r} - f_k f_{k+r} \}^2.$$

We consider the terms I and II separately. We first obtain a bound for $\mathbb{E}|I^2|$. Observe that $\mathbb{E}|I^2| = 3(\mathbb{E}|I_1^2| + \mathbb{E}|I_2^2|)$, where

$$\begin{aligned} I_1 &= \frac{1}{\sqrt{T}} \sum_k \frac{J_k \bar{J}_{k+r}}{(f_k f_{k+r})^{3/2}} \{ \hat{f}_k \hat{f}_{k+r} - \mathbb{E}(\hat{f}_k \hat{f}_{k+r}) \} \\ I_2 &= \frac{1}{\sqrt{T}} \sum_k \frac{J_k \bar{J}_{k+r}}{(f_k f_{k+r})^{3/2}} \{ \mathbb{E}(\hat{f}_k \hat{f}_{k+r}) - f_k f_{k+r} \}, \end{aligned}$$

hence we will obtain the bounds $\mathbb{E}(I_1^2)$ and $\mathbb{E}(I_2^2)$. Expanding $\mathbb{E}(I_1^2)$ and using Lemma A.6(i) and that $f_{k_1} f_{k_1+r}$ is bounded away from zero gives

$$\mathbb{E}(I_1^2) \leq \frac{1}{T} \sum_{k_1, k_2} \frac{1}{(f_{k_1} f_{k_1+r} f_{k_2} f_{k_2+r})^{3/2}} \frac{C}{bT} \left\{ \frac{1}{|k_1 - k_2|^2} + \frac{\log T}{T} \right\} = O\left(\frac{1}{bT}\right). \quad (25)$$

Expanding $\mathbb{E}|I_2^2|$ gives

$$\begin{aligned} \mathbb{E}(I_2^2) &\leq \frac{C}{T} \sum_{k_1, k_2} \frac{1}{(f_{k_1} f_{k_1+r} f_{k_2} f_{k_2+r})^{3/2}} \mathbb{E}(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r}) \times \\ &\quad \left(\mathbb{E}\{ \hat{f}_{k_1} \hat{f}_{k_1+r} \} - f_{k_1} f_{k_1+r} \right) \left(\mathbb{E}\{ \hat{f}_{k_2} \hat{f}_{k_2+r} \} - f_{k_2} f_{k_2+r} \right). \end{aligned} \quad (26)$$

The bounds for $\mathbb{E}|I_2^2|$ differ slightly, depending on the assumption. Under Assumption 3.1, by using Brillinger (1981), Theorem 4.3.2, it can be shown that $\mathbb{E}(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r}) = O(T^{-1})$ (since $r \neq 0$). Moreover, by using Lemma A.6(iii) we have $\mathbb{E}\{ \hat{f}_{k_1} \hat{f}_{k_1+r} \} - f_{k_1} f_{k_1+r} = O(b + (bT)^{-1})$. Therefore under Assumption 3.1 we have

$$\mathbb{E}(I_2^2) = O\left((b + \frac{1}{bT})^2\right). \quad (27)$$

Therefore, under Assumption 3.1, using (25) and (27) gives $\mathbb{E}|I|^2 = O(\frac{1}{bT} + (b + \frac{1}{bT})^2)$ and

$$I = O_p(b + \frac{1}{bT} + \frac{1}{\sqrt{bT}}). \quad (28)$$

On the other hand, under Assumption 4.1 we do not have that $\mathbb{E}(J_{k_1} \bar{J}_{k_1+r} \bar{J}_{k_2} J_{k_2+r}) = O(T^{-1})$, instead we substitute Lemma A.6(iv) into (26) and obtain

$$\mathbb{E}(I_2^2) = O(\{\frac{T}{r^2} + 1\}(b^2 + \frac{1}{bT})^2). \quad (29)$$

Therefore, under Assumption 4.1, using (25) and (29) gives $\mathbb{E}|I|^2 = O(\frac{1}{bT} + (\frac{T}{r^2} + 1)(b^2 + \frac{1}{bT})^2)$ and

$$I = O_p\left(\frac{1}{\sqrt{bT}} + (\frac{\sqrt{T}}{|r|} + 1)(b^2 + \frac{1}{bT})\right). \quad (30)$$

We now obtain a bound for II . Since the spectral density $f(\omega)$ is bounded away from zero and $\sup_{\omega} |\hat{f}_T(\omega) - f(\omega)| \xrightarrow{P} 0$ (see (Paparoditis, 2009), Lemma 6.1(ii)), we have $II = O_p(\tilde{II})$, where

$$\tilde{II} = \frac{1}{\sqrt{T}} \sum_k (J_k \bar{J}_{k+r} \{\hat{f}_k \hat{f}_{k+r} - f_k f_{k+r}\}^2).$$

To obtain a bound for $\tilde{II}$ we use that $|\tilde{II}| \leq 3\tilde{II}_1 + 3\tilde{II}_2$, where

$$\tilde{II}_1 = \frac{1}{\sqrt{T}} \sum_k (|J_k \bar{J}_{k+r}| \{\hat{f}_k \hat{f}_{k+r} - \mathbb{E}(\hat{f}_k \hat{f}_{k+r})\}^2) \text{ and } \tilde{II}_2 = \frac{1}{\sqrt{T}} \sum_k (|J_k \bar{J}_{k+r}| \{\mathbb{E}(\hat{f}_k \hat{f}_{k+r}) - f_k f_{k+r}\}^2).$$

Using Cauchy-Schwarz inequality, Lemma A.6(ii,iv) we have

$$\mathbb{E}|\tilde{II}_1| \leq \frac{1}{\sqrt{T}} \sum_k \mathbb{E}(|J_k \bar{J}_{k+r}|^2)^{1/2} (\mathbb{E}\{\hat{f}_k \hat{f}_{k+r} - \mathbb{E}(\hat{f}_k \hat{f}_{k+r})\}^4)^{1/2} = O(\frac{T^{1/2}}{bT} (\frac{1}{|r|} + \frac{1}{T^{1/2}})).$$

We now obtain a bound for $\mathbb{E}|\tilde{II}_2|$. Using Lemma A.6(iii,iv) we have

$$\mathbb{E}(\tilde{II}_2) \leq \frac{1}{\sqrt{T}} \sum_k \mathbb{E}(|J_k \bar{J}_{k+r}|^2)^{1/2} \{\mathbb{E}(\hat{f}_k \hat{f}_{k+r}) - f_k f_{k+r}\}^2 = O(\sqrt{T}(b + \frac{1}{bT})^2 (\frac{1}{|r|} + \frac{1}{T^{1/2}})).$$

Therefore

$$\tilde{II} = O\left(\left(\frac{1}{|r|} + \frac{1}{T^{1/2}}\right) \frac{1}{bT^{1/2}} + b^2 T^{1/2} + \frac{1}{b^2 T^{5/2}} + T^{-1/2}\right). \quad (31)$$

Hence (31) and (28) give (23) and (31) and (30) give (24). $\square$

A.3 The variance and expectation of the covariance $\tilde{c}_T(r)$

A.3.1 Under the null

It is straightforward to show, under Assumption 3.1, that $\mathbb{E}(\sqrt{T}\tilde{c}_T(r)) = O(T^{-1/2})$. We now obtain the asymptotic variance of the $\tilde{c}_T(r)$ under the null of stationarity. We mention that the following two lemmas apply to nonlinear time series too.

The following lemma immediately follows from (Brillinger, 1981), Theorem 4.3.2. We use this result to obtain the asymptotic variance of $\tilde{c}_T(r)$, below.

Lemma A.8 *Let $\{X_t\}$ be a stationary time series where we denote the second and fourth order cumulants as κ_2 and κ_4 . Suppose $\sum_k (1 + |k|)|\kappa_2(k)| < \infty$ and $\sum_{k_1, k_2, k_3} (1 + |k_i|)|\kappa_4(k_1, k_2, k_3)| < \infty$. Then we have*

$$\begin{aligned} \text{cov}(J_{k_1}J_{k_2}, J_{k_3}J_{k_4}) &= \left(\frac{f(\omega_{k_1})}{T} \sum_{t=1}^T e^{it\omega_{k_1}-k_3} + O\left(\frac{1}{T}\right) \right) \left(\frac{f(\omega_{k_2})}{T} \sum_{t=1}^T e^{it\omega_{k_2}-k_4} + O\left(\frac{1}{T}\right) \right) \\ &\quad + \left(\frac{f(\omega_{k_1})}{T} \sum_{t=1}^T e^{it\omega_{k_1}-k_4} + O\left(\frac{1}{T}\right) \right) \left(\frac{f(\omega_{k_2})}{T} \sum_{t=1}^T e^{it\omega_{k_2}-k_3} + O\left(\frac{1}{T}\right) \right) \\ &\quad + (2\pi)f_4(\omega_{k_1}, \omega_{k_2}, -\omega_{k_3}) \frac{1}{T^2} \sum_{t=1}^T e^{it\omega_{k_1}+k_2-k_3-k_4} + O\left(\frac{1}{T^2}\right). \end{aligned} \quad (32)$$

Lemma A.9 *Suppose the assumptions in Lemma A.8 hold. Then we have*

$$\begin{aligned} &\text{cov}(\sqrt{T}\Re\tilde{c}_T(r_1), \sqrt{T}\Re\tilde{c}_T(r_2)) = \text{cov}(\sqrt{T}\Im\tilde{c}_T(r_1), \sqrt{T}\Im\tilde{c}_T(r_2)) \\ &= \begin{cases} O(T^{-1}) & r_1 \neq r_2 \\ 1 + \frac{1}{2} \frac{2\pi}{2T^2} \sum_{k_1, k_2=1}^T g_{T, k_1}^{(r)} g_{T, k_2}^{(r)} f_4(\omega_{k_1}, -\omega_{k_1+r}, -\omega_{k_2}) + O\left(\frac{1}{T}\right) & r_1 = r_2 = r \end{cases} \end{aligned} \quad (33)$$

Furthermore if the tri-spectra $f_4(\omega_1, \omega_2, \omega_3)$ is Lipschitz continuous we have

$$\begin{aligned} &\text{cov}(\sqrt{T}\Re\tilde{c}_T(r_1), \sqrt{T}\Re\tilde{c}_T(r_2)) = \text{cov}(\sqrt{T}\Im\tilde{c}_T(r_1), \sqrt{T}\Im\tilde{c}_T(r_2)) \\ &= \begin{cases} O(T^{-1}) & r_1 \neq r_2 \\ 1 + \frac{1}{4\pi} \int_0^{2\pi} \int_0^{2\pi} \frac{f_4(\omega_1, -\omega_1-\omega_r, -\omega_2)}{\sqrt{f(\omega_1)f(\omega_1+\omega_r)f(\omega_2)f(\omega_2+\omega_r)}} d\omega_1 d\omega_2 + O\left(\frac{1}{T}\right) & r_1 = r_2 = r \end{cases} \end{aligned} \quad (34)$$

and for all r_1, r_2 , $\text{cov}(\sqrt{T}\Re\tilde{c}_T(r_1), \sqrt{T}\Im\tilde{c}_T(r_2)) = O\left(\frac{1}{T}\right)$.

PROOF. To prove the result we use that $\Re\tilde{c}_T(r) = \frac{1}{2}(\tilde{c}_T(r) + \bar{\tilde{c}}_T(r))$ and $\Im\tilde{c}_T(r) = \frac{-i}{2}(\tilde{c}_T(r) - \bar{\tilde{c}}_T(r))$, and evaluate $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$, $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\bar{\tilde{c}}_T(r_2))$ and $\text{cov}(\sqrt{T}\bar{\tilde{c}}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$.

Expanding $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$ gives

$$\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2)) = \frac{1}{T} \sum_{k_1, k_2=1}^T g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} \text{cov}(J_{k_1} \bar{J}_{k_1+r_1}, J_{k_2} \bar{J}_{k_2+r_2}),$$

where $g_{T,k}^{(r)} = f(\omega_k)^{-1/2} f(\omega_k + \omega_r)^{-1/2}$. Substituting (32) into the above it is easy to show that for $r_1 \neq r_2$ we have $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2)) = O(T^{-1})$ and for $r := r_1 = r_2$ we have

$$\begin{aligned} & \text{cov}(\sqrt{T}\tilde{c}_T(r), \sqrt{T}\tilde{c}_T(r)) \\ &= \frac{2}{T} \sum_{k=1}^T (g_{T,k}^{(r)})^2 f(\omega_k) f(\omega_{k+r}) + \frac{1}{T^2} \sum_{k_1, k_2=1}^T g_{T,k_1}^{(r)} g_{T,k_2}^{(r)} f_4(\omega_{k_1}, -\omega_{k_1+r}, -\omega_{k_2}) + O\left(\frac{1}{T}\right) \\ &= 2 + \frac{2\pi}{T^2} \sum_{k_1, k_2=1}^T g_{T,k_1}^{(r)} g_{T,k_2}^{(r)} f_4(\omega_{k_1}, -\omega_{k_1+r}, -\omega_{k_2}) + O\left(\frac{1}{T}\right). \end{aligned}$$

The same method gives us a similar bound for $\text{cov}(\sqrt{T}\tilde{c}_T(r), \sqrt{T}\tilde{c}_T(r))$. Similarly it can be shown that unless $r_2 = T - r_1$ we have $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2)) = O(T^{-1})$. Also, for $r_1 \neq r_2$ we have $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2)) = O(T^{-1})$. Altogether this gives us (33).

We now obtain (34) by using (33) and replacing the sum with an integral. By using that the spectral density and tri-spectra $f(\cdot)$ and $f_4(\cdot)$ are Lipschitz continuous we can replace the summand above with an integral to give

$$\text{cov}(\sqrt{T}\tilde{c}_T(r), \sqrt{T}\tilde{c}_T(r)) = 2 + \frac{1}{2\pi} \int_0^\pi \int_0^\pi \frac{f_4(\omega_1, -\omega_1 - \omega_r, -\omega_2)}{\sqrt{f(\omega_1) f(\omega_1 + \omega_r) f(\omega_2) f(\omega_2 + \omega_r)}} d\omega_1 d\omega_2 + O\left(\frac{1}{T}\right).$$

A similar result can be obtained for $\text{cov}(\sqrt{T}\tilde{c}_T(r), \sqrt{T}\tilde{c}_T(r))$. Substituting the above into (33) gives (34). $\square$

Lemma A.10 *Suppose Assumption 3.1 holds. Then the spectral density $f(\omega)$ and the phase function $\phi(\omega)$, satisfy $\sup_\omega |f'(\omega)| < \infty$ and $\sup_\omega |\phi'(\omega)| < \infty$.*

PROOF. The fact that $\sup_\omega |f'(\omega)| < \infty$ follows immediately from Assumption 3.1(i). To prove that $\sup_\omega |\phi'(\omega)| < \infty$ we recall that $\phi(\omega) = \arctan \frac{\Im A(\omega)}{\Re A(\omega)}$. Differentiating $\phi(\omega)$ with respect to ω and using the chain rule gives

$$\frac{d\phi(\omega)}{d\omega} = \frac{1}{1 + \left(\frac{\Im A(\omega)}{\Re A(\omega)}\right)^2} \times \frac{1}{[\Re A(\omega)]^2} \left(\Im A(\omega) \frac{d\Re A(\omega)}{d\omega} - \Re A(\omega) \frac{d\Im A(\omega)}{d\omega} \right).$$

Under Assumption 3.1(i,iii) we have $\inf_\omega \Re A(\omega) > 0$, $\sup_\omega |A(\omega)| < \infty$ and $\sup_\omega \left| \frac{dA(\omega)}{d\omega} \right| < \infty$. Therefore $\sup_\omega \left| \frac{d\phi(\omega)}{d\omega} \right| < \infty$. Thus giving the required result. $\square$

PROOF of Lemma 3.1 We use Lemma A.9 to prove the result. We note that Assumption 3.1 satisfy the assumptions in Lemma A.9. Therefore we have the identity in (33). However in the case that the time series is linear this expression can be simplified. It is well know that for a linear time series the tri-spectra can be written in terms of the transfer function $A(\omega)$ that is

$$f_4(\omega_1, \omega_2, \omega_3) = \frac{\kappa_4}{2\pi} A(\omega_1) A(\omega_2) A(\omega_3) A(-\omega_1 - \omega_2 - \omega_3).$$

Now we recall that for a linear time series $A(\omega) = \sqrt{f(\omega)} \exp(i\phi(\omega))$ hence substituting this into the ratio in (33) gives

$$2\pi \frac{f_4(\omega_{k_1}, -\omega_{k_2} - \omega_r, -\omega_{k_2})}{\sqrt{f(\omega_{k_1})f(\omega_{k_1} + \omega_2)f(\omega_{k_2})f(\omega_{k_2} + \omega_r)}} = \kappa_4 \exp(i[\phi(\omega_{k_1}) - \phi(\omega_{k_1} + \omega_r) - \phi(\omega_{k_2}) + \phi(\omega_{k_2} + \omega_r)]).$$

Substituting the above into (33) gives

$$\text{cov}(\tilde{c}_T(r), \tilde{c}_T(r)) = 1 + \frac{\kappa_4}{2} \left| \frac{1}{T} \sum_k \exp(i[\phi_k - \phi_{k+r}]) \right|^2.$$

Finally we note that due to Lemma A.10, the phase $\phi(\cdot)$ is Lipschitz continuous, hence $\exp(i\phi(\omega))$ is Lipschitz continuous, and we can replace the summand in the above with an integral to give

$$\text{cov}(\tilde{c}_T(r), \tilde{c}_T(r)) = \sigma^2 + \frac{\kappa_4}{2} \left| \frac{1}{2\pi} \int_0^{2\pi} \exp(i[\phi(\omega) - \phi(\omega + \frac{2\pi r}{T})]) d\omega \right|^2 + O(\frac{1}{T}).$$

This completes the proof. □

A.3.2 The alternative of local stationarity

We now consider some of the moment properties of $\tilde{c}_T(r)$ under the assumption of local stationarity.

Lemma A.11 *Suppose Assumption 4.1 holds. Then we have*

$$\begin{aligned} \text{cov}(J_{k_1} J_{k_2}, J_{k_3} J_{k_4}) &= \{F_2(k_1 - k_3; \omega_{k_1}) F_2(k_2 - k_4; \omega_{k_2}) + F_2(k_1 - k_4; \omega_{k_1}) F_2(k_2 - k_3; \omega_{k_2})\} \\ &+ \frac{(2\pi)}{T} F_4(k_1 + k_2 - k_3 - k_4; \omega_{k_1}, \omega_{k_2}, -\omega_{k_3}) \\ &+ O\left(\frac{(\log T)^3}{T^2} + \frac{\log T}{T} (F_2(k_1 - k_3; \omega_{k_1}) + F_2(k_2 - k_4; \omega_{k_2}) + \right. \\ &\quad \left. F_2(k_1 - k_4; \omega_{k_1}) + F_2(k_2 - k_3; \omega_{k_2}))\right), \end{aligned} \tag{35}$$

where $\{F_2(\cdot; \omega)\}$ and $\{F_4(\cdot; \omega_{k_1}, \omega_{k_2}, \omega_{k_3})\}$ are defined in (20).

PROOF. Expanding $\text{cov}(J_{k_1} J_{k_2}, J_{k_3} J_{k_4})$ in terms of cumulants gives

$$\text{cov}(J_{k_1} J_{k_2}, J_{k_3} J_{k_4}) = \text{cov}(J_{k_1}, \bar{J}_{k_3})\text{cov}(J_{k_2}, \bar{J}_{k_4}) + \text{cov}(J_{k_1}, \bar{J}_{k_4})\text{cov}(J_{k_2}, \bar{J}_{k_3}) + \text{cum}(J_{k_1}, J_{k_2}, \bar{J}_{k_3}, \bar{J}_{k_4}),$$

finally substituting Corollary A.1 into the above gives the result. $\square$

PROOF of Lemma 4.1 equations (12) and (13) We first prove (12). We note that from the definition of $\hat{f}_T(\omega_k)$ in (1) and under Assumption 4.1 we have

$$|\mathbb{E}(\hat{f}_T(\omega_k)) - f(\omega_k)| = \left| \sum_j \frac{1}{bT} K\left(\frac{\omega_k - \omega_j}{b}\right) \mathbb{E}(|J_T(\omega_j)|^2) - f(\omega_k) \right| = O(b^2). \quad (36)$$

We now obtain $\text{var}(\hat{f}_T(\omega_k))$. We observe that

$$\text{var}(\hat{f}_T(\omega_k)) = \sum_{j_1, j_2} \frac{1}{(bT)^2} K\left(\frac{\omega_k - \omega_{j_1}}{b}\right) K\left(\frac{\omega_k - \omega_{j_2}}{b}\right) \text{cov}(|J_T(\omega_{j_1})|^2, |J_T(\omega_{j_2})|^2).$$

Now we substitute (35) into the above to give

$$\begin{aligned} \text{var}(\hat{f}_T(\omega_k)) &\leq C \sum_{j_1, j_2} \frac{1}{(bT)^2} K\left(\frac{\omega_k - \omega_{j_1}}{b}\right) K\left(\frac{\omega_k - \omega_{j_2}}{b}\right) \{ |F_2(j_1 - j_2; \omega_{j_1}) F_2(j_2 - j_1; \omega_{j_1})| + \\ &\quad |F_2(j_2 - j_1; \omega_{j_1}) F_2(j_1 - j_2; -\omega_{j_1})| + \frac{2\pi}{T} F_4(0; \omega_{j_1}, -\omega_{j_1}, \omega_{j_2}) \} + O\left(\frac{(\log T)^3}{T^2}\right). \end{aligned}$$

We observe from the above that the covariance terms dominate the fourth order cumulant term. Moreover, by using Lemma A.2 we have $\sup_\omega \sum_s |F_2(s; \omega)| < \infty$, which gives $\text{var}(\hat{f}_T(\omega_k)) = O(\frac{1}{bT})$. This together with (36) gives (12).

We now prove (13). Using Lemma A.4 for $n = 2$ gives

$$\mathbb{E}(\tilde{c}_T(r)) = \frac{1}{T} \sum_{k=1}^T \frac{1}{[f(\omega_k) f(\omega_k + \omega_r)]^{1/2}} \frac{1}{T} \sum_{t=1}^T f\left(\frac{t}{T}, \omega_k\right) \exp(-it\omega_r) + O\left(\frac{\log T}{T}\right). \quad (37)$$

Now by using replacing sum with integral and using Lemma A.3 (noting

$F_{2,T}(-r; \omega_k) = \frac{1}{T} \sum_{t=1}^T f\left(\frac{t}{T}, \omega_k\right) \exp(-it\omega_r)$ and $F_2(-r; \omega_k) = \int_0^1 f(u, \omega_k) \exp(-i2\pi r u) du$) gives

$$\mathbb{E}(\tilde{c}_T(r)) = \frac{1}{2\pi} \int_0^1 \int_0^{2\pi} \frac{f(u, \omega)}{[f(\omega) f(\omega + \omega_r)]^{1/2}} \exp(-i2\pi r u) du d\omega + O\left(\frac{\log T}{T} + \frac{1}{T^2}\right), \quad (38)$$

thus we have (13). $\square$

To prove (14) in Lemma 4.1, we evaluate the limiting variance of $\tilde{c}_T(t)$ under the alternative of local stationarity.

Lemma A.12 *Suppose Assumption 4.1 holds. Then we have*

$$\text{cov}(\Re\sqrt{T}\tilde{c}_T(r_1), \Re\sqrt{T}\tilde{c}_T(r_2)) = \frac{1}{4}(\Gamma_{T,r_1,r_2}^{(1)} + \Gamma_{T,r_1,r_2}^{(2)} + \Gamma_{T,r_2,r_1}^{(2)} + \Gamma_{T,r_1,r_2}^{(3)}) + O\left(\frac{\log T}{T}\right), \quad (39)$$

$$\text{cov}(\Re\sqrt{T}\tilde{c}_T(r_1), \Im\sqrt{T}\tilde{c}_T(r_2)) = \frac{-i}{4}(\Gamma_{T,r_1,r_2}^{(1)} + \Gamma_{T,r_1,r_2}^{(2)} - \Gamma_{T,r_2,r_1}^{(2)} - \Gamma_{T,r_1,r_2}^{(3)}) + O\left(\frac{\log T}{T}\right),$$

$$\text{cov}(\Im\sqrt{T}\tilde{c}_T(r_1), \Im\sqrt{T}\tilde{c}_T(r_2)) = \frac{1}{4}(\Gamma_{T,r_1,r_2}^{(1)} - \Gamma_{T,r_1,r_2}^{(2)} - \Gamma_{T,r_2,r_1}^{(2)} + \Gamma_{T,r_1,r_2}^{(3)}) + O\left(\frac{\log T}{T}\right),$$

where

$$\begin{aligned} \Gamma_{T,r_1,r_2}^{(1)} &= \frac{1}{T} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} \{F_2(k_1 - k_2; \omega_{k_1}) F_2(-k_1 - r_1 + k_2 + r_2; -\omega_{k_1+r_1}) + \\ &F_2(k_1 + k_2 + r_2; \omega_{k_1}) F_2(-k_1 - r_1 - k_2; -\omega_{k_1+r_1})\} + \frac{1}{T^2} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} F_4(r_2 - r_1; \omega_{k_1}, -\omega_{k_1+r_1}, -\omega_{k_2}), \\ \Gamma_{T,r_1,r_2}^{(2)} &= \frac{1}{T} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} \{F_2(k_1 + k_2; \omega_{k_1}) F_2(-k_1 - r_1 - k_2 - r_2; -\omega_{k_1+r_1}) + \\ &F_2(k_1 - k_2 - r_2; \omega_{k_1}) F_2(-k_1 - r_1 + k_2; -\omega_{k_1+r_1})\} + \frac{1}{T^2} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} F_4(-r_2 - r_1; \omega_{k_1}, -\omega_{k_1+r_1}, -\omega_{k_2}), \\ \Gamma_{T,r_1,r_2}^{(3)} &= \frac{1}{T} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} \{F_2(-k_1 + k_2; -\omega_{k_1}) F_2(k_1 + r_1 - k_2 - r_2; \omega_{k_1+r_1}) + \\ &F_2(-k_1 - k_2 - r_2; -\omega_{k_1}) F_2(k_1 + r_1 + k_2; \omega_{k_1+r_1})\} + \frac{1}{T^2} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} F_4(r_1 - r_2; -\omega_{k_1}, \omega_{k_1+r_1}, -\omega_{k_2}), \end{aligned}$$

and the coefficients $F_2(\cdot)$ and $F_4(\cdot)$ are defined in (20) and $g_{T,k}^{(r)} = \{f(\omega_k) f(\omega_{k+r})\}^{-1/2}$.

PROOF. To prove (39) we use $\Re\tilde{c}_T(r) = \frac{1}{2}(\tilde{c}_T(r) + \bar{\tilde{c}}_T(r))$ and $\Im\tilde{c}_T(r) = \frac{-i}{2}(\tilde{c}_T(r) - \bar{\tilde{c}}_T(r))$, and $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\bar{\tilde{c}}_T(r_2))$ and $\text{cov}(\sqrt{T}\bar{\tilde{c}}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$. Expanding $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$ we have

$$\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2)) = \frac{1}{T} \sum_{k_1,k_2} g_{T,k_1}^{(r_1)} g_{T,k_2}^{(r_2)} \text{cov}(J_{k_1} \bar{J}_{k_1+r_1}, J_{k_2} \bar{J}_{k_2+r_2}),$$

now by substituting (35) into the above we obtain

$$\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2)) = \Gamma_{T,r_1,r_2}^{(1)} + O\left(\frac{\log T}{T}\right).$$

Similar results can be obtained for $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$ and $\text{cov}(\sqrt{T}\tilde{c}_T(r_1), \sqrt{T}\tilde{c}_T(r_2))$. Using this we obtain the required result. $\square$

PROOF of Lemma 4.1, equation (14) This immediately follows from Lemma A.12. $\square$

A.4 Asymptotic normality

In this section we prove asymptotic normality of $\sqrt{T}\tilde{c}_T(r)$. Since the locally stationary linear time series model includes the stationary time series model as a special case we show asymptotic normality of the more general locally stationary model. We start by approximating $\sqrt{T}\tilde{c}_T(r)$ with a random variable which only involves current innovations $\{\varepsilon_t\}_{t=1}^T$. We make this approximation in order to use the martingale central limit theorem to prove asymptotic normality of $\sqrt{T}\tilde{c}_T(r)$. In this section, we will make frequent appeals to Lemma A.1.

Using that the locally stationary time series model $X_{t,T}$ satisfies (10) we have can write $\sqrt{T}\tilde{c}_T(r)$ as

$$\begin{aligned} & \sqrt{T}\tilde{c}_T(r) \\ &= \frac{1}{T^{3/2}} \sum_{k=1}^T \frac{1}{f(\omega_k)^{1/2} f(\omega_k + \omega_r)^{1/2}} \sum_{t,\tau=1}^T \exp(i(t-\tau)\omega_k) \exp(-i\tau\omega_r) \sum_{j_1, j_2=0}^{\infty} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) \varepsilon_{t-j_1} \varepsilon_{\tau-j_2} \\ &= \frac{1}{T^{1/2}} \sum_{t,\tau=1}^T G_{T,\omega_r}(t-\tau) \exp(-i\tau\omega_r) \sum_{j_1, j_2=0}^{\infty} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2})), \end{aligned}$$

where $\{G_{T,\omega_r}(s)\}$ is the DFT defined in (15).

We now partition $\sqrt{T}\tilde{c}_T(r)$ into terms which involve ‘present’ and ‘past’ innovation, that is

$$\sqrt{T}(\tilde{c}_T(r) - \mathbb{E}(\tilde{c}_T(r))) = \sqrt{T}(d_T(r) + V_T(r)), \quad (40)$$

where

$$\begin{aligned} d_T(r) &= \frac{1}{T} \sum_{t,\tau=1}^T G_{T,\omega_r}(t-\tau) \exp(-i\tau\omega_r) \sum_{0 \leq j_1 \leq t-1} \sum_{0 \leq j_2 \leq \tau-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2})) \\ V_T(r) &= \frac{1}{T} \sum_{t,\tau=1}^T G_{T,\omega_r}(t-\tau) \exp(-i\tau\omega_r) \sum_{j_1 \geq t-1 \text{ or } j_2 \geq \tau-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2})). \end{aligned}$$

In the following lemma we obtain a bound for the remainder $V_T(r)$. Later we will show asymptotic normality of $d_T(r)$.

Lemma A.13 *Suppose Assumption 4.1 hold. Then we have*

$$(T^{1/2}\mathbb{E}|V_T(r)|^2)^{1/2} \leq CT^{-1/2},$$

for some finite constant C .

PROOF. We first observe that $\sqrt{T}V_T(r) = I_1 + I_2 + I_3$, where

$$I_1 = \frac{1}{T^{1/2}} \sum_{t,\tau=1}^T G_{T,\omega_r}(t-\tau) \exp(-i\tau\omega_r) \sum_{j_1 \geq t-1} \sum_{0 \leq j_2 \leq \tau-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2}))$$

$$I_2 = \frac{1}{T^{1/2}} \sum_{t,\tau=1}^T G_{T,\omega_r}(t-\tau) \exp(-i\tau\omega_r) \sum_{j_2 \geq \tau-1} \sum_{0 \leq j_1 \leq t-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2}))$$

$$I_3 = \frac{1}{T^{1/2}} \sum_{t,\tau=1}^T G_{T,\omega_r}(t-\tau) \exp(-i\tau\omega_r) \sum_{j_2 \geq \tau-1} \sum_{j_1 \geq t-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2})).$$

We first show that $\mathbb{E}(I_1^2)^{1/2} = O(T^{-1/2})$. By the Minkowski's inequality we have

$$\mathbb{E}(I_1^2)^{1/2} \leq \frac{1}{T^{1/2}} \sum_{t,\tau=1}^T |G_{T,\omega_r}(t-\tau)| \left\{ \mathbb{E} \left(\sum_{j_1 \geq t-1} \sum_{0 \leq j_2 \leq \tau-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2})) \right)^2 \right\}^{1/2}.$$

It can be shown that

$$\begin{aligned} & \mathbb{E} \left(\sum_{j_1 \geq t-1} \sum_{0 \leq j_2 \leq \tau-1} \psi_{t,T}(j_1) \psi_{\tau,T}(j_2) (\varepsilon_{t-j_1} \varepsilon_{\tau-j_2} - \mathbb{E}(\varepsilon_{t-j_1} \varepsilon_{\tau-j_2})) \right)^2 \\ & \leq (\text{var}(\varepsilon_t)^2 + \text{var}(\varepsilon_t^2)) \left[\sum_{j_1 \geq t} |\psi_{t,T}(j_1)|^2 \right] \left[\sum_{j_2=0}^{\infty} |\psi_{\tau,T}(j_2)|^2 \right]. \end{aligned}$$

Substituting this into the bound for $\mathbb{E}(I_1^2)$, under Assumption 4.1 and using Lemma A.1 we have

$$\begin{aligned} \mathbb{E}(I_1^2)^{1/2} & \leq \frac{1}{T^{1/2}} \sup_{\tau} \left[\sum_{j_2=0}^{\infty} |\psi_{\tau,T}(j_2)|^2 \right]^{1/2} \left[\sum_{s=1}^T |G_{T,\omega_r}(s)| \right] \sum_{t=1}^T \left[\sum_{j_1 \geq t} |\psi_{t,T}(j_1)|^2 \right]^{1/2} \\ & \quad \frac{1}{T^{1/2}} \sup_{\tau} \left[\sum_{j_2=0}^{\infty} |\psi_{\tau,T}(j_2)|^2 \right]^{1/2} \left[\sum_{s=1}^T |G_{T,\omega_r}(s)| \right] \sum_{t=1}^T \sum_{j_1 \geq t} |\psi_{t,T}(j_1)| = O(T^{-1/2}). \end{aligned}$$

Using a similar method we can show that $\mathbb{E}(I_2^2)^{1/2} = O(T^{-1/2})$ and $\mathbb{E}(I_3^2)^{1/2} = O(T^{-1/2})$. Thus we obtain the result. $\square$

Therefore the above lemma shows that $\sqrt{T}(\tilde{c}_T(r) - \mathbb{E}(\tilde{c}_T(r))) = \sqrt{T}d_T(r) + O_p(T^{-1/2})$.

Remark A.1 *Now it is worth noting that in the case that $\{X_t\}$ is a stationary linear time series, then $d_T(r)$ has an interesting form. That is, it is straightforward to show (using (Priestley, 1981), Theorem 6.2.1) that*

$$\sqrt{T}\tilde{c}_T(r) = \frac{1}{\sqrt{T}} \sum_{k=1}^T J_\varepsilon(\omega_k) \overline{J_\varepsilon(\omega_{k+r})} \exp(i(\phi(\omega_k) - \phi(\omega_{k+r}))) + O_p(T^{-1/2}),$$

where $J_\varepsilon(\omega) = (2\pi T)^{-1/2} \sum_{t=1}^T \varepsilon_t \exp(it\omega_k)$.

We use the martingale central limit theorem to show asymptotic normality of $\sqrt{T}d_T(r)$, which will imply asymptotic normality of $\sqrt{T}(\tilde{c}_T(r) - \mathbb{E}(\tilde{c}_T(r)))$. To do this we rewrite $\sqrt{T}d_T(r)$ as the sum of martingale differences

$$\begin{aligned} & \sqrt{T}d_T(r) \\ &= \frac{1}{T^{1/2}} \sum_{s_1, s_2=1}^T (\varepsilon_{s_1}\varepsilon_{s_2} - \mathbb{E}(\varepsilon_{s_1}\varepsilon_{s_2})) \sum_{s_1 \leq t \leq T} \sum_{s_2 \leq \tau \leq T} G_{T, \omega_r}(t - \tau) \exp(-i\tau\omega_r) \psi_{t,T}(t - s_1) \psi_{\tau,T}(\tau - s_2) \\ &= \frac{1}{T^{1/2}} \sum_{s=1}^T M_T(s) \quad \text{where} \quad M_T(s) = (\varepsilon_s^2 - 1)A_T(s, s) + \varepsilon_s \sum_{s_1=1}^{s-1} \varepsilon_{s_1} (A_T(s_1, s) + A_T(s_1, s)) \end{aligned}$$

and

$$A_T(s_1, s_2) = \sum_{s_1 \leq t \leq T} \sum_{s_2 \leq \tau \leq T} G_{T, \omega_r}(t - \tau) \exp(-i\tau\omega_r) \psi_{t,T}(t - s_1) \psi_{\tau,T}(\tau - s_2).$$

We now show that the coefficients in the martingale differences are absolutely summable.

Lemma A.14 *Suppose Assumption 4.1 holds. Then we have*

$$\sup_T \sum_{s_1=1}^{s-1} (|A_T(s, s_1)| + |A_T(s_1, s)|) < \infty.$$

PROOF. To prove the result we note that under Assumption 4.1 and using Lemma A.1 we have

$$\begin{aligned} \sum_{s_1=1}^{s-1} |A_T(s_1, s)| &\leq \sum_{s_1=1}^{s-1} \sum_{s_1 \leq t \leq T} \sum_{s \leq \tau \leq T} |G_{T, \omega_r}(t - \tau)| \cdot |\psi_{t, T}(t - s_1)| \cdot |\psi_{\tau, T}(\tau - s)| \\ &\leq \left[\sum_t |G_{T, \omega_r}(t)| \right] \sup_{t, T} \left[\sum_s |\psi_{t, T}(s)| \right]^2, \end{aligned}$$

which gives the required result. $\square$

In the theorem below we show asymptotic normality of $d_T(r)$. To accommodate both the stationary and nonstationary case we will let the asymptotic variance of $d_T(r)$ be V_r and specify its value later.

Theorem A.2 *Suppose Assumption 4.1 holds. Furthermore suppose that $\text{var}(\sqrt{T}d_T(r), \sqrt{T}d_T(r)) \rightarrow V_r < \infty$ as $T \rightarrow \infty$. Then we have*

$$\sqrt{T} \begin{pmatrix} \Re \sqrt{T}d_T(r) \\ \Im \sqrt{T}d_T(r) \end{pmatrix} \xrightarrow{D} \mathcal{N}(0, V_r).$$

PROOF. We use the martingale central limit theorem to prove the result. We will show asymptotic normality of $\Re \sqrt{T}d_T(r)$. However, using the same method it is straightforward to show asymptotic normality for all linear combinations of $\Re \sqrt{T}d_T(r)$ and $\Im \sqrt{T}d_T(r)$ and thus by the Cramer-Wold device to show asymptotic normality of the random vector $(\Re \sqrt{T}d_T(r), \Im \sqrt{T}d_T(r))$. Let $M_{1, T} = \Re M_T(s)$. To apply the martingale central limit theorem we need to verify that the variance of $T^{-1/2} \sum_{d=1}^T M_{1, T}(s)$ is finite (which is assumed), Lindeberg's condition is satisfied and $\frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1, T}(s)^2 | \mathcal{F}_{s-1}) \xrightarrow{P} V_{r, 1}$ (see (Hall & Heyde, 1980), Theorem 3.2). To verify Lindeberg's condition, we require that for all $\delta > 0$,

$$L_T = \frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1, T}(s)^2 I(T^{-1/2} |M_{1, T}(s)| > \delta) | \mathcal{F}_{s-1}) \xrightarrow{P} 0,$$

$T \rightarrow \infty$, where $I(\cdot)$ is the identity function and $\mathcal{F}_s = \sigma(M_{1, T}(s), M_{1, T}(s-1), \dots, M_{1, T}(1))$. By using Hölder and Markov inequalities, we obtain a bound for the following L_T

$$L_T \leq (T\delta)^{-1} \frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1, T}(s)^4 | \mathcal{F}_{s-1}). \quad (41)$$

Now by using Lemma A.14 we have $\sum_{s_1} (|A_T(s, s_1)| + |A_T(s_1, s)|) < \infty$, therefore

$$\sup_T \mathbb{E} \left(\frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1, T}(s)^4 | \mathcal{F}_{s-1}) \right) = \frac{1}{T} \sup_T \sum_{s=1}^T \mathbb{E}(M_{1, T}(s)^4) < \infty.$$

Since $\frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1,T}(s)^4 | \mathcal{F}_{s-1})$ is a positive random variable, the above result implies $\frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1,T}(s)^4 | \mathcal{F}_{s-1}) = O_p(1)$. Substituting this into (41) gives $L_T \xrightarrow{P} 0$ as $T \rightarrow \infty$.

Finally we need to show that

$$\frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1,T}(s)^2 | \mathcal{F}_{s-1}) = \frac{1}{T} \sum_{s=1}^T [\mathbb{E}(M_{1,T}(s)^2 | \mathcal{F}_{s-1}) - \mathbb{E}(M_{1,T}(s)^2)] + \frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1,T}(s)^2) \xrightarrow{P} V_{r,1}. \quad (42)$$

Under the stated assumptions, we have $\frac{1}{T} \sum_{s=1}^T \mathbb{E}(M_{1,T}(s)^2) \rightarrow V_{r,1}$ as $T \rightarrow \infty$. Therefore it remains to show

$$P_T := \frac{1}{T} \sum_{s=1}^T |\mathbb{E}(M_{1,T}(s)^2 | \mathcal{F}_{s-1}) - \mathbb{E}(M_{1,T}(s)^2)| \xrightarrow{P} 0,$$

which will give us (42). We will show that $\mathbb{E}(P_T^2) \rightarrow 0$. To do this we note that $\mathbb{E}(P_T) = 0$ and

$$\text{var}(P_T) = \frac{1}{T^2} \sum_{d=1}^T \text{var}(\mathbb{E}(M_{1,T}(s)^2 | \mathcal{F}_{s-1})) + \frac{2}{T^2} \sum_{s_1 > s_2}^T \text{cov}(\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_1-1}), \mathbb{E}(M_{1,T}(s_2)^2 | \mathcal{F}_{s_2-1})). \quad (43)$$

Now by using the Cauchy Schwartz inequality and conditional expectation arguments for $\mathcal{F}_{s_2} \subset \mathcal{F}_{s_1}$ we have

$$\begin{aligned} & \text{cov}(\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_1-1}), \mathbb{E}(M_{1,T}(s_2)^2 | \mathcal{F}_{s_2-1})) \\ & \leq [\mathbb{E}(\mathbb{E}(M_{1,T}(s_2)^2 | \mathcal{F}_{s_2-1}) - \mathbb{E}(M_{1,T}(s_2)^2))^2]^{1/2} [\mathbb{E}(\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_2-1}) - \mathbb{E}(M_{1,T}(s_1)^2))^2]^{1/2}. \end{aligned}$$

We now show that $\sup_T \sum_{s_1=s_2}^T [\mathbb{E}(\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_2-1}) - \mathbb{E}(M_{1,T}(s_1)^2))^2]^{1/2} < \infty$. Let $\mathcal{G}_s = \sigma(\varepsilon_s, \varepsilon_{s-1}, \dots)$, then it is clear that for all s , $\mathcal{F}_s \subset \mathcal{G}_s$. Therefore, we have $\mathbb{E}[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_2-1})^2] \leq \mathbb{E}[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{G}_{s_2-1})^2]$ which gives

$$\begin{aligned} \mathbb{E} \left[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_2-1}) - \mathbb{E}(M_{1,T}(s_1)^2) \right]^2 &= \mathbb{E}[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{F}_{s_2-1})^2] - [\mathbb{E}(M_{1,T}(s_1)^2)]^2 \\ &\leq \mathbb{E}[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{G}_{s_2-1})^2] - [\mathbb{E}(M_{1,T}(s_1)^2)]^2. \end{aligned}$$

Expanding $M_{1,T}(s_1)$ in terms of $\{\varepsilon_t\}$ and using $\sup_{T,t} \sum_j |\psi_{t,T}(j)| < \infty$, it can be shown that $\mathbb{E}[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{G}_{s_2-1})^2] - [\mathbb{E}(M_{1,T}(s_1)^2)]^2 \rightarrow 0$ as $s_1 \rightarrow \infty$, and

$$\text{var}(P_T) \leq \frac{1}{T} \sum_{s_2=1}^T \sup_{s_2, T} \sum_{s_1=s_2}^T (\mathbb{E}[\mathbb{E}(M_{1,T}(s_1)^2 | \mathcal{G}_{s_2-1})^2] - [\mathbb{E}(M_{1,T}(s_1)^2)]^2)^{1/2} < \infty.$$

Substituting the above into (44) we have $\text{var}(P_T) = O(T^{-1})$, hence we have shown (42), and the conditions of the martingale central limit theorem are satisfied, giving the required result. $\square$

Proof of Theorem 3.2 Using Lemma 3.1 we have

$$\begin{aligned} \sqrt{T} \left(\Re \tilde{c}_T(r_1), \dots, \Im \tilde{c}_T(r_m) \right) &= \sqrt{T} \left(\Re \hat{c}_T(r_1), \dots, \Im \hat{c}_T(r_m) \right) + \\ &O_p \left(m \left[\left(b + \frac{1}{\sqrt{bT}} \right) + \left(\frac{1}{bT^{1/2}} + b^2 T^{1/2} \right) \sum_{n=1}^m \left(\frac{1}{|r_n|} + \frac{1}{T^{1/2}} \right) \right] \right). \end{aligned}$$

Lemma 3.1, implies that $T \text{var} \left(\Re \hat{c}_T(r_1), \dots, \Im \hat{c}_T(r_m) \right) \rightarrow \text{diag}(1 + \frac{1}{2} \kappa_4 \varphi(\frac{r_1}{T}), \dots, \text{diag}(1 + \frac{1}{2} \kappa_4 \varphi(\frac{r_m}{T}))$.
Combining this with a similar proof to the proof of Theorem A.2, gives

$$\sqrt{T} \left(\frac{1}{1 + \frac{1}{2} \kappa_4 \varphi(\frac{r_1}{T})} \Re \tilde{c}_T(r_1), \dots, \frac{1}{1 + \frac{1}{2} \kappa_4 \varphi(\frac{r_m}{T})} \Im \tilde{c}_T(r_m) \right) \xrightarrow{D} \mathcal{N}(0, I_{2m}). \quad (44)$$

Finally, since $m(b + \frac{1}{\sqrt{bT}}) + (\frac{1}{bT^{1/2}} + b^2 T^{1/2}) \sum_{n=1}^m (\frac{1}{|r_n|} + \frac{1}{T^{1/2}}) \rightarrow 0$, using (44) we have (9). $\square$

PROOF of Theorem 4.2. The proof is identical to the proof of Theorem 3.2. Hence we omit the details. $\square$

References

- Adak, S. (1998). Time dependent spectral analysis of a time series. *J. American Statistical Association*, 93, 1488-1501.
- Andreou, E., & Ghysels, E. (2008). Structural breaks in financial time series. In T. G. Anderson, R. A. Davis, J.-P. Kreiss, & T. Mikosch (Eds.), *Handbook of financial time series* (p. 839-866). Berlin: Springer.
- Berkes, I., Gombay, E., & Horváth, L. (2009). Testing for changes in the covariance structure of linear processes. *J. Statistical Planning and Inference*, 139, 2044-2063.
- Briggs, W., & Henson, V. E. (1997). *The DFT: An owner's manual for the discrete fourier transform*. SIAM.
- Brillinger, D. (1981). *Time series, data analysis and theory*. San Francisco: SIAM.
- Brillinger, D., & Rosenblatt, M. (1967). Asymptotic theory of estimates of k-th order spectra. *Proceedings of the National Academy of Sciences, USA*, 57, 206-210.
- Brockwell, P. J., & Davis, R. A. (1987). *Time series: Theory and methods*. New York: Springer.
- Chen, W., & Deo, R. (2004). A generalized Portmanteau goodness of fit test for time series. *Econometric Theory*, 20, 382-416.

- Cho, H., & Fryzlewicz, P. (2009). Multiscale and multilevel technique for consistent segmentation of nonstationary time series. *Preprint*.
- Dahlhaus, R. (1997). Fitting time series models to nonstationary processes. *Ann. Statist.*, *16*, 1-37.
- Dahlhaus, R., & Polonik, W. (2006). Nonparametric quasi-maximum likelihood estimation for gaussian locally stationary processes. *Ann. Stat.*, *34*, 2790-2824.
- Giraitis, L., & Leipus, R. (1992). Testing and estimating in the change point problem of the spectral density. *Lithuanian Mathematical Journal*, *32*, 15-29.
- Hall, P., & Heyde, C. (1980). *Martingale Limit Theory and its Application*. New York: Academic Press.
- Kokoszka, P., & Mikosch, T. (2000). The periodogram at the fourier frequencies. *Stochastic processes and their applications*, *86*, 49-79.
- Loretan, M., & Philips, P. C. B. (1994). Testing the covariance stationarity of heavy tailed time series. *J. Empirical Finance*, *1*, 211-248.
- Nason, G., & Sachs, R. von. (1999). Wavelets in time series analysis. *Phil. Trans. R. Soc. Lond. A*, *2511-2526*, 357.
- Nason, G., Sachs, R. von, & Kroisandt, G. (2000). Wavelet processes and adaptive estimation of the evolutionary wavelet spectrum. *J. Royal Statistical Society (B)*, *62*, 271-292.
- Ozaki, T., & Tong, H. (1975). On the fitting of non-stationary models in time series. In *Proceedings of the 8th Hawaii International Conference on System Science* (p. 224-226). Western Periodical Company.
- Paparoditis, E. (2009). Testing temporal constancy of the spectral structure of a time series. *To appear in Bernoulli*.
- Picard, D. (1985). Testing and estimating change points in time series. *Advances in time series analysis*, *17*, 841-867.
- Priestley, M. B. (1981). *Spectral analysis and time series*. London: Academic Press.
- Priestley, M. B., & Subba Rao, T. (1969). A test for non-stationarity of a time series. *J. Roy. Stat. (B)*, *31*, 140-149.
- Robinson, P. (1989). Nonparametric estimation of time-varying parameters. In P. Hackl (Ed.), *Statistical analysis and Forecasting of Economic Structural Change* (p. 253-264). Berlin: Springer.

Sachs, R. von, & Neumann, M. H. (1999). A wavelet-based test for stationarity. *Journal of Time Series Analysis*, *21*, 597-613.

Subba Rao, T. (1970). The fitting of non-stationary time-series models with time-dependent parameters. *J. R. Statist. Soc. B*, **32**, 312-22.